


Page	Title of schematic page	Rev.	Date
01	Page List	3A	03/15
02	Block Diagram	3A	
03	CPU-Champlain HT/CONTROL (1/3)	3A	03/15
04	CPU-Champlain MEMORY (2/3)	3A	03/15
05	CPU-Champlain POWER/GND (3/3)	3A	
06	NB-RS880M HT/SP-MEM (1/4)	3A	03/15
07	NB-RS880M GFX/PCIE (2/4)	3A	
08	NB-RS880M SYSTEM (3/4)	3A	03/15
09	NB-RS880M POWER (4/4)	3A	03/15
10	SB-SB820M PCI/CLK/LPC (1/4)	3A	03/15
11	SB-SB820M AUDIO/USB (2/4)	3A	03/15
12	SB-SB820M SATA (3/4)	3A	
13	SB-SB820M POWER (4/4)	3A	03/15
14	DDR3 SODIMM* 2 (5.2mm+9.2mm)	3A	
15	ATI-M92 XTX PCIE/LVDS (1/5)	3A	
16	ATI-M92 XTX Main I/O (2/5)	3A	03/15
17	ATI-M92 XTX Power/GND (3/5)	3A	03/15
18	ATI-M92 XTX Display POWER (4/5)	3A	03/15
19	ATI-M92 XTX MEM I/F (5/5)	3A	03/15
20	ATI-M92 XTX VRAM-B DDR3	3A	
21	CRT/LVDS	3A	03/15
22	HDMI	3A	03/15

Page	Title of schematic page	Rev.	Date
23	WLAN/HDD/ODD	3A	03/15
24	Card Reader RTS5186	3a	03/15
25	Express Card/BT/LED	3A	03/15
26	Codec-ALC269Q VB5 GR	3A	03/15
27	LAN RTL8111E	3A	03/15
28	NPCE781	3A	03/15
29	KB/USB/FAN/PS	3A	
30	VCORE(ISL6265A)	3A	03/15
31	3VPCU&5VPCU(PM6686)	3A	03/15
32	1.5VSUS/VTT_MEM	3A	03/15
33	DYN_VCC1.1(OZ8116LN)	3A	03/15
34	VCC1.1(OZ8116LN)-7A	3A	03/15
35	VGA_CORE(OZ8116)-16A	3A	03/15
36	VCC1.8/0.9/2.5/1.0	3A	03/15
37	POWER(BAT IN / ADA IN/ UL)	3A	03/15
38	CHARGER (ISL6252A)	3A	03/15
39	Small board connector	3A	03/15
40	Decoupling(Cap)	3A	03/15
41	Power Sequence	3A	
42	CHANGE LIST	3A	03/15

1.Level 1 Environment-related Substances Should NEVER be Used.
2.Purchase ink, paint, wire rods, and Molding resins only from the business Partners that Sony approves as Green Partners.


 Quanta Computer Inc. PROJECT : NE7		Rev 3A
AMD Danube		
Date:	Monday, March 22, 2010	Sheet 1 of 42



Processor Memory Interface

CPU_VDDR : 35W->0.9V
45W->1.05V




3A delete R208 0ohm



Quanta Computer Inc.
PROJECT : NE7

Size	Document Number	Rev
		3A
Date	Monday, March 22, 2010	Sheet 4 of 42

1.Level 1 Environment-related Substances Should NEVER be Used.
2.Purchase ink, paint, wire rods, and Molding resins only from the business Partners that Sony approves as Green Partners.






1



 Quanta Computer Inc. PROJECT : NE7				Rev 3/
Size	Document Number	RS880M HT/SPMEM(1/4)		
Date:	Monday, March 22, 2010	Sheet	6 of	42



Layout Swap
 TX11, TX10, TX9,
 TX8, TX7, TX6, TX5,
 TX4, TX3, TX2, TX0

GLAN

WLAN






Quanta Computer Inc.


PROJECT : NE7

Size	Document Number	Rev
	RS880M GFX/PCIE(2/4)	3A
Date:	Monday, March 22, 2010	Sheet 7 of 42

- Level 1 Environment-related Substances Should NEVER be Used.
- Purchase ink, paint, wire rods, and Molding resins only from the business Partners that Sony approves as Green Partners.






Enables Debug Bus access through memory I/O pads and GPIO.
0 : Enable RS880M, Default
1 : Disable RS880M



Discrete : Connect
A11, B11



Indicates if memory Side port is available or not
1: Disable side port memory
0: Enable side port memory





1. Level 1 Environment-related Substances Should NEVER be Used.
2. Purchase ink, paint, wire rods, and Molding resins only from the business Partners that Sony approves as Green Partners.

 Quanta Computer Inc. PROJECT : NE7		Rev 3A
Size	Document Number	
Date: Monday, March 22, 2010	Sheet	8 of 42

hexainf@hotmail.com
GRATIS - FREE

RTC




Quanta Computer Inc.
PROJECT : NE7

Size


Document Number	35
-----------------	----

Number


4.1.3

Rev
3A

1. Level 1 Environment-related Substances Should NEVER be Used.
2. Purchase ink, paint, wire rods, and Molding resins only from the business Partners that Sony approves as Green Partners.




	GPIO200, GPIO199
PULL HIGH	H, H=Reserved H, L=SPI ROM
PULL LOW	L, H=LPC ROM(Default) L, L=FWH ROM



GPIO[150:128] are open drain GPIO pins where as GP0160 is an open drain GPO pin. These pins are not programmed to GPIO mode by default.

ID2	ID1	ID0	
0	0	0	Danube UMA
0	0	1	Danube UMA+Side port
0	1	0	Danube+Park XT
0	1	1	Danube+Madison LP
1	0	0	Danube+M92 XTX
1	0	1	
1	1	0	
1	1	1	

	NON	SAMSUNG	HYNIX	
SP ID0	0	1	0	1
SP ID1	0	0	1	1



1.Level 1 Environment-related Substances Should NEVER be Used.
2.Purchase ink, paint, wire rods, and Molding resins only from the business Partners that Sony approves as Green Partners.



Quanta Computer Inc.
PROJECT : NE7


Size Document Number Rev 3A
SB820 SATA(2/4)

Date: Monday, March 22, 2010 Sheet 12 of 42


3A change R172, L42, L28, L25 to short pad

3A change R150, L27, L26, L30 to short pad








Place these Caps near So-Dimm1.



Place these Caps near So-Dimm0.





Quanta Computer Inc.
PROJECT : NE7

Size	Document Number	Rev
	DDR3 SODIMMX2	3A
Date	Monday, March 22, 2010	Sheet 14 of 42

hexainf@hotmail.com
GRATIS - FREE

1. Level 1 Environment-related Substances Should NEVER be Used.
2. Purchase ink, paint, wire rods, and Molding resins only from the business Partners that Sony approves as Green Partners.



Dual channel support

Single channel support

Madison M2

Madison M2

1.Level 1 Environment-related Substances Should NEVER be Used.


2.Purchase ink, paint, wire rods, and Molding resins only from the business Partners that Sony approves as Green Partners.




Quanta Computer Inc.



PROJECT : NE7

Size	Document Number	Rev
	ATI PCIE/LVDS	3A
Date:	Monday, March 22, 2010	Sheet 15 of 42






**Use this option ONLY
for Park-S3**






LVDS






1.Level 1 Environment-related Substances Should NEVER be Used.
2.Purchase ink, paint, wire rods, and Molding resins only from the business Partners that Sony approves as Green Partners.

 Quanta Computer Inc. PROJECT : NE7		Size	Document Number	Rev
			HDMI	3A
Date:	Monday, March 22, 2010	Sheet	22	of 42




Win7 didn't support wake WLAN


3A change R252 to short pad. Hunson: Remove short pad: R252




WLAN_BT_SW



SATA ODD



2.5 inch SATA HDD





Quanta Computer Inc.
PROJECT : NE7


Size	Document Number	Rev
	WLAN/HDD/ODD	3A
Date	Monday, March 22, 2010	Sheet 23 of 42

1. Level 1 Environment-related Substances Should NEVER be Used.
2. Purchase ink, paint, wire rods, and Molding resins only from the business Partners that Sony approves as Green Partners.

Bluetooth




RF LED




3A : Reverse C786, C787, C788 FP for ESD

Card LED





HDD LED



3A : adding Q30 for ESD.

Battery LED






I/O Address				
*	BADDR1-0		Index	Data
	1 0		2E	2F
	1 1		4E	4F
	0 0		(HCFGBAH, HCFGBAL)	(HCFGBAH, HCFGBAL)+1
	0 1		XOR-TREE TEST	

SHMB: SHMB(If = 0 Enable share host BIOS memory)

DOCK_RST# : BADDR0
T7: BADDR1

Reserved for more EC wake up function



Issue after RVCCON 20-25ms

Power step3
Power step1

3A add R489 10 k PD


3A change TP to cpu_prochot# in EC.

BATT_SCK R236 4.7K 4
BATT_SDA R307 4.7K 4
FUN_ASSIST# R304 10K 4


Power step4

Power step5

Adding for ICT



EC SDI-> EEprom D0
EC SDO-> EEprom D1




Quanta Computer Inc.
PROJECT : NE7
NPCE781 & FLASH





Size	Document Number	Rev
		3A
Date	Monday, March 22, 2010	Sheet 28 of 42

1.Level 1 Environment-related Substances Should NEVER be Used.
2.Purchase ink, paint, wire rods, and Molding resins only from the business Partners that Sony approves as Green Partners.


KEYBOARD



USB Port + e-SATA(USB)




FAN




ISL6265 Pin1	OFS	VFIXEN
1.2V	V	X
3.3V	X	V
5V	X	X

VFIXEN VID Codes		
SVC	SVD	Output
0	0	1.4
0	1	1.2
1	0	1.0
1	1	0.8





1.Level 1 Environment-related Substances should NEVER be Used.
2.Purchase ink, paint, wire rods, and Molding resins only from the business Partners that Sony approves as Green Partners.



2. Purchase ink, paint, wire rods, and Molding resins only from the business Partners that Sony approves as Green Partners

1.5VSUS & VTT_MEM




MODE	DISCHARGE MODE
+5V	No discharge
+1.8V	Tracking discharge
GND	Non-tracking discharge

VDDQSET	VDDQ(V)	VTTREF & VTT	NOTE
GND	1.5 fixed	VDDQSNS/2	DDR3
5V	1.8 fixed	VDDQSNS/2	DDR2
FB-Resistor	Adjustable	VDDQSNS/2	1.5V<VDDQ<3V

$$V_{TT} = V_{TTREF} = V_{DDQSNS}/2 = 0.75V$$

STATE	S3	S5	1.5VSUS	VTTREF	VTT
S0	1	1	on	on	on
S3	0	1	on	on	off
S4/S5	0	0	off	off	off



VCC_NB should not ramp before 1.1v
(RC=-22ms)

PR118 change to 47K,
DYN_VCC1.1 output 1.25V
(RS880M->Enhanced mode)

Jerry change footprint to be 50723_213-3-2



DYN_PWR_EN	High	Low
DYN_VCC1.1	0.95V	1.1V




Quanta Computer Inc.
PROJECT : NE7
DYN_VCC1.1(OZ8116LN)

Size	Document Number	Rev
		3A
Date:	Monday, March 22, 2010	Sheet 33 of 42





1.Level 1 Environment-related Substances Should NEVER be Used.
2.Purchase ink, paint, wire rods, and Molding resins only from the business Partners that Sony approves as Green Partners.





**M92**



External VGA_CORE Voltage Setting:

V_PWRCNTL0	VGA_CORE
0	1.20V
1	0.95V













MB to TP connector




WLAN

BT


1.8V MOS



MB to LED board




MB to USB board




3A change from 88511-3001 to 88707-3001

Decoupling Cap

40



Power ripple



1.Level 1 Environment-related Substances Should NEVER be Used.
2.Purchase ink, paint, wire rods, and Molding resins only from the business Partners that Sony approves as Green Partners.




Quanta Computer Inc.
PROJECT : NE7

Size	Document Number	Rev
	Decoupling Cap	3A
Date:	Monday, March 22, 2010	Sheet 40 of 42

SB800:

- 1, +3.3VDUAL ramp before +1.1VDUAL
- 2, +3.3v ramp before +1.8v
- 3, +1.8V ramp before +1.1v
- 4, +3.3v ramp before +1.1v
- 5, +3.3VALW_R ramping down time > 300us
- 6, 50uS <= All power rails except +3.3VALW_R <= 40mS
- 7, 100uS <= +3.3VALW_R <= 40mS

RS880:
1, 0 < (+3.3V) - (+1.8v) < 2.1
2, +1.8V ramp before +1.1v
3. +1.1V ramp before VCC_NB



2A Adding R159 (10K) for shut down issue.

3A Rename for location(R464, C452)

3A Delete AMD debug connector

3A change R169, R155, R162, R340, R163, R161, R168, R341, R337 to short pad

3A Delete R332, R249, R181, R333 0ohm

3A change L23, L24, L29, L21, R156, R171, R167 to short pad

3A Delete R427, R428, R429, R430 0ohm.

3A delete RP36, RP42, RP38, RP26, RP43, RP41, RP35 0ohm

3A : Delete R358 0ohm

3A : change R247, R305 from 100k to 10Kohm

3A : change R196, R198 from 100k to 10Kohm

3A change R150, L27, L26, L30 to short pad

3A change R172, L42, L28, L25 to short pad

3A change R309, R184, L31, L34, L41 to short pad

3A change L32, L33, L35, R212 to short pad

3A Adding GPIO3 ` 4 for VGA thermal sensor

3A : change L3004, L3019 to short pad

3A change L3006, L3010 to short pad

3A delete L3007, L3012, L3013, R3061 0ohm

3A delete R3049 0ohm

3A change R3112 to short pad

3A delete R3113 0ohm

3A change R252 to short pad.

3A change MR2, MR3, MR8, MR9, MR10, MR11, MR12, MR13, MR14, MR15, MR16, MR17, MR18, ML1 to short pad.

3A : adding Q30 for ESD.

3A Change R214 to short pad

3A: delete R277, R294 0ohm

3A: Change L36, L37, L38, L39 to short pad

3A delete R290, R295(colayout) 0ohm, T74(EC side)

3A C541, C542, C543 change from AGND to GND

3A R375 no mount

3A delete LR14 0ohm

3A change LR6 to short pad

3A change R478 to short pad

3A adding R485 PD for mute

Remove short pad: R422,R423



Quanta Computer Inc.

PROJECT : NE7

Size	Document Number	Rev
	Change History	3A
Date:	Monday, March 22, 2010	Sheet 42 of 42

1.Level 1 Environment-related Substances Should NEVER be Used.
2.Purchase ink, paint, wire rods, and Molding resins only from the business Partners that Sony approves as Green Partners.