


SX7 SYSTEM DIAGRAM



01


PCB STACK UP

LAYER 1 : TOP
LAYER 2 : GND
LAYER 3 : IN1
LAYER 4 : IN2
LAYER 5 : VCC
LAYER 6 : BOT




PROJECT : SX7
Quanta Computer Inc.

Size Custom Document Number Block Diagram Rev 3A
Date: Monday, March 15, 2010 Sheet 1 of 43



CLOCKS name	Discrete	Clock pin function
NBGF_X_CLKP NBGF_X_CLKN	NA	to NB for VGA reference clock
EXT_GFX_CLKP EXT_GFX_CLKN	RP21 STUFF	to Park-S3 external reference clock -Discrete only
SBLINK_CLKP SBLINK_CLKN	RP26 STUFF	to NB for AC-LINK reference clock
CLK_VGA_27M_SS CLK_VGA_27M_NSS	R441, R442 STUFF	To Park-S3 27Mhz - Discrete only


Need check the net name for the short pad



IDT ICS9LPRS480AKLFT--ALPRS480000
SLG SLG8SP628VTR--AL8SP628000
RTL RTM880N-796-- AL000880001

* default

SEL_HTT66	1	66 MHz 3.3V single ended HTT clock
	0*	100 MHz differential HTT clock
SEL_SATA	1	100 MHz non-spreading differential SRC clock
	0*	100 MHz spreading differential SRC clock
SEL_27	1*	27MHz non-spreading singled clock
	0	100 MHz spreading differential SRC clock



Clock chip has internal serial terminations for differential pairs, external resistors are reserved for debug purpose.




PROJECT : SX7
Quanta Computer Inc.







across plane splits








modify PV



PROJECT : SX7
Quanta Computer Inc.


Size Custom	Document Number DDR2 SODIMMS TERMINATIONS	Rev 3A
Date: Monday, March 15, 2010	Sheet 7 of 43	



signals	RS880M
HT_TXCALP	R430 301 ohm 1%
HT_TXCALN	
HT_RXCALP	R434 301 ohm 1%
HT_RXCALN	

65






PROJECT : SX7
Quanta Computer Inc.

Size
Custom

Document Number
RS880M-PCIE I/F 2I5

Rev
3A

Date: Monday, March 15, 2010 Sheet 9 of 43




```

Enables Debug Bus access
through memory I/O pads and GPIO.
0 : Enable RS880M , Default
1 : Disable RS880M
(RX881 use DAC VSYNC)

```


Discrete



Indicates if memory Side port
is available or not


0: Reserved HSYNC INT
1: Required setting. Select with a pull-up
resistor on the strap
(RX881 use DAC HSYNC)

Discrete



RX881/RS880 POWER DIFFERENCE TABLE

PIN NAME	RX881	RS880	PIN NAME	RX881	RS880
VDDHT	+1.1V	+1.1V	IOPLLVD	+1.1V	+1.1V
VDDHTRX	+1.1V	+1.1V	AVDD	GND	+3.3V
VDDHTTX	+1.2V	+1.2V	AVDDDI	GND	+1.8V
VDDA18PCIE	+1.8V	+1.8V	AVDDQ	GND	+1.8V
VDDG18	+1.8V	+1.8V	PLLVD	GND	+1.1V
VDD18_MEM	GND	+1.8V	PLLVD18	GND	+1.8V
VDDPCIE	+1.1V	+1.1V	VDDA18PCIEPLL	+1.8V	+1.8V
VDDC	+1.1V	+1.1V	VDDA18HTPLL	+1.8V	+1.8V
VDD_MEM	GND	+1.8V/1.5V	VDDLTP18	GND	+1.8V
VDDG33	+3.3V	+3.3V	VDDL18	GND	+1.8V
IOPLLVD18	+1.8V	+1.8V	VDDL18	NC	NC



PART 5/6

POWER



NB5/RD2

PROJECT : SX7
Quanta Computer Inc.


Size
CustomDocument Number
RS880M-POWER5/5Rev
3A

Date: Monday, March 15, 2010 Sheet 11 of 43

NC only ,Can't be install




+3V SCL0/SDATA0 is 3V tolerance
AMD datasheet define it




Clock gen/CPU thermal
/DDR3/DDR3
thermal/Accelerometer

+3V5 SCL1/SDATA1 is 3V/S5 tolerance
AMD datasheet define it





+3V5 SCL2/SDATA2 is 3V/S5 tolerance
AMD datasheet define it





+3V modify PV



modify MV





To Azalia




Remove short pad

To Modem Board




Remove short pad


modify DB2




modify DB2



modify DB2




modify MV



modify DB2



modify PV




modify DB2




modify PV




modify DB2



modify PV







modify DB2






*SW JTAG DEBUG










SB800 Part 4 of 5














ACPI / WAKE UP EVENTS





USBCLK/14M_25M_48M_OSC



USB 1.1 USB MISC






for EMI



PROJECT : SX7
Quanta Computer Inc.

Size	Document Number	Rev
Custom	SB820-ACPI/GPIO/USB 2/4	3A
Date: Monday, March 15, 2010	Sheet 13 of 43	

SATA PORT 0,1,2,3
can support AHCI
mode



SB800

Part 2 of 5

FLASH

SERIAL ATA

HW MONITOR

SPI ROM

SATA_TX0P
SATA_TX0N
SATA_RX0N
SATA_RX0P
SATA_TX1P
SATA_TX1N
SATA_RX1N
SATA_RX1P
SATA_TX2P
SATA_TX2N
SATA_RX2N
SATA_RX2P
SATA_TX3P
SATA_TX3N
SATA_RX3N
SATA_RX3P
SATA_TX4P
SATA_TX4N
SATA_RX4N
SATA_RX4P
SATA_TX5P
SATA_TX5N
SATA_RX5N
SATA_RX5P
SATA_CALRP
SATA_CALRN
SATA_ACT#/GPIO67
SATA_X1
SATA_X2
SPI_DI/GPIO164
SPI_DO/GPIO163
SPI_CLK/GPIO162
SPI_CS1#/GPIO165
ROM_RST#/GPIO161

FC_CLK
FC_FBCLKOUT
FC_FBCLKIN
FC_OE#/GPIO145
FC_AVD#/GPIO146
FC_WE#/GPIO148
FC_CE1#/GPIO149
FC_CE2#/GPIO150
FC_INT1/GPIO144
FC_INT2/GPIO147
FC_ADQ0/GPIO128
FC_ADQ1/GPIO129
FC_ADQ2/GPIO130
FC_ADQ3/GPIO131
FC_ADQ4/GPIO132
FC_ADQ5/GPIO133
FC_ADQ6/GPIO134
FC_ADQ7/GPIO135
FC_ADQ8/GPIO136
FC_ADQ9/GPIO137
FC_ADQ10/GPIO138
FC_ADQ11/GPIO139
FC_ADQ12/GPIO140
FC_ADQ13/GPIO141
FC_ADQ14/GPIO142
FC_ADQ15/GPIO143

WLAN_OFF#
BT_OFF
WWAN_OFF#
WWAN_DET#

CRD REQ1#

MB_THRMDA_SB
TEMP_COMM

ACCELD_EN

SIDE_PORT_ID0
SIDE_PORT_ID1
BOARD_ID0
BOARD_ID1
BOARD_ID2
BOARD_ID3

G27
Y2

SB800 A11

SB800 A11

SB800 A11

SB800 A11

SB800 A11

SB800 A11

SB800 A11

SB800 A11

SB800 A11

SB800 A11

SB800 A11

SB800 A11

SB800 A11

SB800 A11

SB800 A11

SB800 A11

SB800 A11

SB800 A11



SB800 A11

ID3	ID2	ID1	ID0	
0	0	0	0	SX7 UMA
0	0	0	1	SX7 UMA
0	0	1	0	SX7 Dis
0	0	1	1	SX7 Dis
0	1	0	0	SX7 UMA DF
0	1	0	1	SX7 UMA DF
0	1	1	0	SX7 Dis DF
0	1	1	1	SX7 Dis DF



PROJECT : SX7
Quanta Computer Inc.


Size Custom Document Number **SB820-ACPI/GPIO/USB 2/4** Rev 3A
Date: Monday, March 15, 2010 Sheet 14 of 43



REQUIRED STRAPS




OVERLAP COMMON PADS WHERE POSSIBLE FOR DUAL-OP RESISTORS.



DEBUG STRAPS

SB800 HAS 15K INTERNAL PU FOR PCI_AD[27:23]



NB_PWRGD_IN:
RS880/RX881 = 1.8V;
Do NOT share it with SB_PWRGD when use Internal Clk Gen (Need SB PLL initialize firstly)


NB/SB POWER GOOD CIRCUIT


AL17SZ17000 IC(5P) NL17SZ17DFT2G(SOT-353) SOT-353
ALUC1G17000 IC OTHER(5P) SN74AUC1G17DBVR(SOT23-5) SOT23-5



PROJECT : SX7
Quanta Computer Inc.

Size Custom Document Number SB820-STRAPS Rev 3A
Date: Monday, March 15, 2010 Sheet 16 of 43






Memory Aperture size

GPIO9 BIOSROM		GPIO13 ROMIDCFG2	GPIO12 ROMIDCFG1	GPIO11 ROMIDCFG0
0	128M	0	0	0
0	256M	0	0	1
0	64M	0	1	0
0	32M	0	1	1
0	512M	1	0	0
0	1G	1	0	1
0	2G	1	1	0
0	4G	1	1	1

It is a shared pin strap with CONFIG[2:0] if BIOS ROM EN is set to 0.




Size Custom	Document Number Park_GND / LVDS/ Straps	Rev 3A
Date: Monday, March 15, 2010		Sheet 19 of 43



PROJECT : SX7
Quanta Computer Inc.

Size	Document Number	Rev
Custom	Park_Power_and_NC	3A
Date: Monday, March 15, 2010	Sheet 20 of 43	

MEMORY INTERFACE




for Park-S3:Use only
for M9x-S3: no support

	M9x-S2/S3	Park-S3
MEM_CALRN0 (J25)	NC	240R
MEM_CALRP0 (K25)	NC	240R
MEM_CALRP1 (J8)	240R	150R
TESTEN2#2 (K7)	NC	0R
R1	NC	10K
R2	0R	51R
R3	2.2K	NC
C1	2.2nF	68pF

240R:CS12402FB03
150R:CS11502FB21


0R:CS00002JB38
680R:CS16802JB27


2.2nF:CH22206KB16
68pF:CH06806JB01





PROJECT : SX7
Quanta Computer Inc.

Size	Document Number	Rev
Custom	Park_MEM_Interface	3A
Date:	Monday, March 15, 2010	Sheet 21 of 43






CRT PORT




PROJECT : SX7
Quanta Computer Inc.



Size Custom	Document Number LCD CONN/LID function	Rev 3A
Date: Monday, March 15, 2010		Sheet 23 of 43





INT. SPEAKER

Note: JACK_SEN# is electrically floating when no jack is inserted and shorted to ground when jack is present.

Headphone Jack**normal CLOSE****EXT Mic Jack****normal CLOSE**

Note: MIC_SEN# is electrically floating when no jack is inserted and shorted to ground when jack is present.




PROJECT : SX7
Quanta Computer Inc.

Size Custom	Document Number HP/MIC/SPK	Rev 3A
Date: Monday, March 15, 2010	Sheet 26 of 43	

NB5/RD2



29




PROJECT : SX7
Quanta Computer Inc.


Size Custom	Document Number EXTERNAL USB X2	Rev 3A
Date: Monday, March 15, 2010	Sheet 29 of 43	

Note:

SD/MMC 4.2	MS	XD
SP0		XD CD#
SP1	SD WP	
SP2	SD CD#	
SP3	SD DAT1	XD D4
SP4		XD D5
SP5	MS BS	XD D3
SP6	MS D1	XD D2
SP7	MS D0	XD D6
SP8	MS D2	XD D7
SP9	MS INS#	XD D8
SP10	MS D3	XD D9
SP11	MS SCLK	XD D1
SP12	MS D4	XD D0
SP13	MS D5	XD WP#
SP14	MS D6	XD RB#
SP15	MS D7	XD WE#
SP16	MS D8	XD RE#
SP17	MS D9	XD ALE
SP18	MS CE#	
SP19	XD CLE	



XD, MMC 4.2 / SD, MS / MSP 7 IN1 CARD READER




PLASTREN CM7S-02 CARD READER SOCKET





PROJECT : SX7
Quanta Computer Inc.



Size Custom Document Number
RTS5159 & CR SOCKET Rev 3A
Date: Monday, March 15, 2010 Sheet 30 of 43


33





modify PV






















PROJECT : SX7
Quantas Computer Inc.


Size Custom	Document Number	Rev 3A
DDR3 (RT8207)		
Date: Monday, March 15, 2010	Sheet 40	of 43

VGA Core & VCC1.1


	PWRCNTL1	PWRCNTL0	V-CORE
	1	1	0.9V
	1	0	0.95V
	0	1	1.05V
	0	0	1.1V



+0.9V +/- 5%
Continue current:1.5A
Peak current:2A



+2.5 Volt +/- 5%
Countinue current: 200mA
Peak current: 600mA




PROJECT : SX7
Quanta Computer Inc.




Size Custom	Document Number VGA Core/+1.8VGFX/1.0VGFX	Rev 3A
Date: Monday, March 15, 2010		Sheet 41 of 43

ISL6265 Pin1	OFS	VFIXEN
1.2V	V	X
3.3V	X	V
5V	X	X

VFIXEN VID Codes

SVC	SVD	Output
0	0	1.4
0	1	1.2
1	0	1.0
1	1	0.8





PROJECT : SX7
Quanta Computer Inc.

Size Custom	Document Number DISCHARGE/3VS5/5VS5/LAN	Rev 3A
Date: Monday, March 15, 2010	Sheet 43 of 43	