

|                                                  |       |
|--------------------------------------------------|-------|
| Cover Sheet                                      | 1     |
| Block Diagram                                    | 2     |
| Clock ICS950218AF & ATA100 IDE CONNECTORS        | 3     |
| mPGA478-B INTEL CPU Sockets                      | 4 - 5 |
| INTEL Brookdale-G GMCH -- North Bridge           | 6 - 8 |
| INTEL ICH4 -- South Bridge                       | 9-10  |
| LPC I/O -- SMC47M157                             | 11    |
| AC'97 Codec / Audio Jack / Front Audio Connector | 12    |
| Audio Amplifier                                  | 13    |
| DDR DIMM1&2 and DDR Terminator Resistor          | 14-15 |
| AGP Slot                                         | 16    |
| PCI SLOT 1                                       | 17    |
| Floppy, KB/MS, Com/Printer Ports                 | 18    |
| USB Connectors                                   | 19    |
| Front Panel , ATX Connectors & 1.5V Regulators   | 20    |
| FWH & CNR Riser                                  | 21    |
| VRM 9.0 Regulator (CPU Power)                    | 22    |
| SMBUS Isolation & FAN                            | 23    |
| Intel 82540EM LAN Controller <b>新增 Ver 0B</b>    | 24    |
| W83302D(MS5) ACPI Controller                     | 25    |
| VGA Connector                                    | 26    |

# GRIFFON

**Version 1.0c**

| MS-6246     | ERP Number       | Function                 |
|-------------|------------------|--------------------------|
| MS-6539-10c | 501/601-6539-01S | Mainboard                |
| MS-6925-100 | 501/605-6925-010 | Power Button/LED board   |
| MS-6977-10A | 505/605-6977-01S | PCI Adapter card         |
| MS-6979-100 | 505/605-6979-01S | Slim type CD-ROM Adapter |

INTEL (R) Brookdale-G Chipset  
Willamette/Northwood 478pin mPGA-B Processor Schematics

## CPU:

**Willamette/Northwood mPGA-478B Processor**

## System Brookdale-G Chipset:

**INTEL GMCH (North Bridge) +  
INTEL ICH4 (South Bridge)**

## On Board Chipset:

**BIOS -- FWH  
AC'97 Codec -- AD1881A  
LPC Super I/O -- SMC47M157  
Clock Generation -- ICS950218AF  
LAN -- 82540EM**

## Expansion Slots:


**AGP SLOT \* 1  
PCI SLOT \* 1**

***Last Schematic Update Date:***

***Tuesday, September 03, 2002***

**Micro Star Restricted Secret**

|                                                                                                                                                   |             |                     |
|---------------------------------------------------------------------------------------------------------------------------------------------------|-------------|---------------------|
| Title                                                                                                                                             | COVER SHEET | Rev                 |
| Document Number                                                                                                                                   | MS-6539N1   | 1.0c                |
| MICRO-STAR INT'L CO., LTD.<br>No. 69 Li-De St, Jung-He City,<br>Taipei Hsien, Taiwan<br><a href="http://www.msi.com.tw">http://www.msi.com.tw</a> |             | Last Revision Date: |
| Sheet                                                                                                                                             |             | 1 of 29             |



Model option table


| Model type | Function | BOM Config | ERP BOM No. |
|------------|----------|------------|-------------|
|            |          |            |             |
|            |          |            |             |
|            |          |            |             |
|            |          |            |             |
|            |          |            |             |

**Micro Star Restricted Secret**

|                                                                                                                                                   |                                                    |       |
|---------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------|-------|
| Title                                                                                                                                             | BLOCK DIAGRAM                                      | Rev   |
| Document Number                                                                                                                                   | MS-6539N1                                          | 1.0c  |
| MICRO-STAR INT'L CO.,LTD.<br>No. 69, Li-De St, Jung-He City,<br>Taipei Hsien, Taiwan<br><a href="http://www.msi.com.tw">http://www.msi.com.tw</a> | Last Revision Date:<br>Tuesday, September 03, 2002 |       |
| Sheet                                                                                                                                             | 2                                                  | of 29 |

## CLOCK GENERATOR BLOCK

\*Trace < 0.5"




## Shut Source Termination Resistors




Trace less 0.2"

49.9ohm for 50ohm M/B impedance

## CLOCK STRAPPING RESISTORS



## Pull-Down Capacitors




used only for EMI issue  
Trace less 0.2"


## PRIMARY IDE BLOCK

## ATA100 IDE CONNECTORS

## 5" Notebook type SECONDARY IDE BLOCK




\* Trace Width : 5mils  
\* Trace Spacing : 7mils  
\* Length(longest)-Length(shortest)<0.5"  
\* Trace Length less than 6"




## Micro Star Restricted Secret

|                                                                                                              |                  |                                                    |
|--------------------------------------------------------------------------------------------------------------|------------------|----------------------------------------------------|
| Title                                                                                                        | Clock & IDE Conn | Rev                                                |
| Document Number                                                                                              | MS-6539N1        | 1.0c                                               |
| MICRO-STAR INT'L CO.,LTD.<br>No. 69 Li-De St, Jung-He City,<br>Taipei Hsien, Taiwan<br>http://www.msi.com.tw |                  | Last Revision Date:<br>Tuesday, September 03, 2002 |
| Sheet                                                                                                        | 3                | of 29                                              |

### CPU SIGNAL BLOCK




### CPU GTL REFERENCE VOLTAGE BLOCK



Every pin put one 220pF cap near it.  
Trace Width 7mils, Space 10mils.  
Keep the voltage divider within  
1.5" of the GETREF pin.

## CPU ITP BLOCK



## CPU STRAPPING RESISTORS




ALL COMPONENTS CLOSE TO CPU

~~Micro Star Restricted Secret~~


|                                                                                                                      |           |                             |
|----------------------------------------------------------------------------------------------------------------------|-----------|-----------------------------|
| Title                                                                                                                |           | Rev                         |
| mPGA478-B Intel CPU Socket Part 1                                                                                    |           |                             |
| Document Number                                                                                                      | MS-6539N1 | 1.0c                        |
| MICRO-STAR INT'L CO.,LTD.                                                                                            |           | Last Revision Date:         |
| No. 69, Li-De St, Jung-Hs City,<br>Taipei Hsien, Taiwan<br><a href="http://www.msi.com.tw">http://www.msi.com.tw</a> |           | Tuesday, September 03, 2002 |
| Sheet                                                                                                                | 4         | of 29                       |

## CPU VOLTAGE BLOCK



Keep the 22uF cap within 0.6" of the CPU pin.  
Trace Width 12mils, Space 10mils.

## CPU DECOUPLING CAPACITORS



**PLACE CAPS WITHIN CPU CAVITY**


Place these caps on south  
side of processor

Place 14 pcs 1206 size cap  
north side of processor


~~Micro Star Restricted Secret~~

|                                                                                                                       |           |                             |
|-----------------------------------------------------------------------------------------------------------------------|-----------|-----------------------------|
| Title                                                                                                                 |           | Rev                         |
| mPGA478-B Intel CPU Socket Part 2                                                                                     |           |                             |
| Document Number                                                                                                       | MS-6539N1 | 1.0c                        |
| MICRO-STAR INT'L CO., LTD.                                                                                            |           | Last Revision Date:         |
| No. 69, Li-De St, Jung-Ho City,<br>Taippei Hsien, Taiwan<br><a href="http://www.msi.com.tw">http://www.msi.com.tw</a> |           | Tuesday, September 03, 2002 |
| Sheet                                                                                                                 | 5         | of 29                       |


\* Length must be matched within +/-0.1" of the Strobe Signals



### GMCH REFERENCE BLOCK



**Place Cap. as Close as possible to  
GMCH , Trace width 12 mils & 10mils space  
Keep the voltage divider within 3" of the  
GMCH pin.**



Place 0.01uF Cap. as Close as possible to GMCH< 0.25"


Trace width 12 mils & 10mils space

**Micro Star Restricted Secret**


|                                                                                                                       |  |                             |  |
|-----------------------------------------------------------------------------------------------------------------------|--|-----------------------------|--|
| Title                                                                                                                 |  | Rev                         |  |
| Brookdale-G GMCH Part 1 (Power, Host, VGA & HUB)                                                                      |  | 1.0c                        |  |
| Document Number                                                                                                       |  | MS-6539N1                   |  |
| MICRO-STAR INT'L CO., LTD.                                                                                            |  | Last Revision Date:         |  |
| No. 69, Li-De St., Jung-Ho City,<br>Taipei Hsien, Taiwan<br><a href="http://www.msi.com.tw">http://www.msi.com.tw</a> |  | Tuesday, September 03, 2002 |  |
| Sheet                                                                                                                 |  | 6 of 29                     |  |








## GMCH DECOUPLING CAPACITOR



Pin A5  
Pin E1  
Pin J1  
Pin N1  
Pin U1

Place decoupling cap  
close to GMCH AGP  
Interface < 0.1"




Pin AA1  
Pin AE1

Place decoupling cap  
close to GMCH  
Hub-Link Interface<  
0.1"




Pin B14  
Pin A15


Place decoupling cap  
close to GMCH DAC  
Interface< 0.1"



Place decoupling cap  
close to GMCH Core  
Logic Interface <  
0.1"




Place decoupling cap  
close to GMCH CPU  
Interface < 250mil  
in the Vtt corridor





Pin AL37  
Pin AU5  
Pin AU9  
Pin AU13  
Pin AU17  
Pin AU25  
Pin AU29  
Pin AU33

Place decoupling cap  
close to GMCH Memory  
Interface < 0.1", with  
18 mil trace width




Place Bulk cap for Cpre Logic,  
AGP & Hub Link Interface



VCC3 - C88 - 0.1u - VCC5

VCC3 - C65 - 0.1u - VCC\_AGP




Place Bulk cap between  
GMCH & DIMM slot

Micro Star Restricted Secret


|                                                                                                               |                                                   |       |
|---------------------------------------------------------------------------------------------------------------|---------------------------------------------------|-------|
| Title                                                                                                         | Brookdale-G GMCH Part 3 (GND)                     | Rev   |
| Document Number                                                                                               | MS-6539N1                                         | 1.0c  |
| MICRO-STAR INT'L CO., LTD.<br>No. 69 Li-De St, Jung-He City,<br>Taipei Hsien, Taiwan<br>http://www.msi.com.tw | Last Revision Date:<br>Monday, September 16, 2002 |       |
| Sheet                                                                                                         | 8                                                 | of 29 |




# ICH4 PCI / HUB LINK / CPU / LAN / INTERRUPT SIGNALS




# ICH4 SMI# SIGNAL



# ICH4 STRAPPING RESISTORS




# ICH4 REFERENCE VOLTAGE



Place Cap. as Close as possible to ICH4 < 0.25"  
Trace width use 12 mils and 10mils space

# ICH4 DECOUPLING CAPACITORS

Place one 0.1u close to ICH4 <100 mil




# Micro Star Restricted Secret


|                                                                                                                     |                                       |                             |
|---------------------------------------------------------------------------------------------------------------------|---------------------------------------|-----------------------------|
| Title                                                                                                               | ICH4 Part 1 (Power,HUB,PCI & CPU I/F) | Rev                         |
| Document Number                                                                                                     | MS-6539N1                             | 1.0c                        |
| MICRO-STAR INT'L CO.,LTD.                                                                                           |                                       | Last Revision Date:         |
| No. 69 Li-De St, Jung-He City,<br>Taipei Hsien, Taiwan<br><a href="http://www.msi.com.tw">http://www.msi.com.tw</a> |                                       | Tuesday, September 03, 2002 |
| Sheet                                                                                                               |                                       | 9 of 29                     |



# 1/2" Notebook type FLOPPY DISK HEADER




AUDIO CODEC  
9708/9756/1885



~~Micro Star Restricted Secret~~


|                                                                                                                                                   |  |                                                      |  |
|---------------------------------------------------------------------------------------------------------------------------------------------------|--|------------------------------------------------------|--|
| <div style="text-align: center;"><b>Micro Star Restricted Secret</b></div>                                                                        |  |                                                      |  |
| Title                                                                                                                                             |  | AC'97 CODEC                                          |  |
| Document Number                                                                                                                                   |  | MS-6539N1                                            |  |
|                                                                                                                                                   |  | Rev 1.0c                                             |  |
| MICRO-STAR INT'L CO.,LTD.<br>No. 69, Li-De St, Jung-He City,<br>Taipei Hsien, Taiwan<br><a href="http://www.msi.com.tw">http://www.msi.com.tw</a> |  | Last Revision Date:<br>Wednesday, September 04, 2002 |  |
| Sheet                                                                                                                                             |  | 12 of 29                                             |  |



Micro Star Restricted Secret

|                                                         |                                 |                            |
|---------------------------------------------------------|---------------------------------|----------------------------|
| Title                                                   | Audio Amplifier & CD Panel Play | Rev                        |
| Document Number                                         | MS-6539N1                       | 1.0c                       |
| MICRO-STAR INT'L CO.,LTD.                               |                                 | Last Revision Date:        |
| No. 69, Li-De St, Jung-He City,<br>Taipei Hsien, Taiwan |                                 | Monday, September 16, 2002 |
| Sheet                                                   | 13                              | of 29                      |
| http://www.msi.com.tw                                   |                                 |                            |


## SYSTEM MEMORY



## CHECK LAYOUT

Keep the voltage divider within 1" of DIMM1.  
Trace width 12 mil with 12 mil space.  
Place 104pF Cap. near the DIMM

**DIMM1**  
Close to North-Bridge



## DDR DIMM SOCKET

SLAVE ADDRESS = 1010010B



DTMM2

~~Micro Star Restricted Secret~~


|                                                                                                                                                   |  |                                                    |  |      |
|---------------------------------------------------------------------------------------------------------------------------------------------------|--|----------------------------------------------------|--|------|
| Title                                                                                                                                             |  | DDR DIMM1&2                                        |  | Rev  |
| Document Number                                                                                                                                   |  | MS-6539N1                                          |  | 1.0c |
| MICRO-STAR INT'L CO.,LTD.<br>No. 69, Li-De St, Jung-Hs City,<br>Taipei Hsien, Taiwan<br><a href="http://www.msi.com.tw">http://www.msi.com.tw</a> |  | Last Revision Date:<br>Tuesday, September 03, 2002 |  |      |
|                                                                                                                                                   |  | Sheet<br>14 of 29                                  |  |      |



## DDR TERMINATORS




## DDR Decoupling Caps



Total 110 signal, need 55 pcs decoupling.

## Place for VTT\_DDR island




## Micro Star Restricted Secret

|                                                                                                               |                         |                                                    |
|---------------------------------------------------------------------------------------------------------------|-------------------------|----------------------------------------------------|
| Title                                                                                                         | DDR Terminator Resistor | Rev                                                |
| Document Number                                                                                               | MS-6539N1               | 1.0c                                               |
| MICRO-STAR INT'L CO.,LTD.<br>No. 69, Li-De St, Jung-He City,<br>Taipei Hsien, Taiwan<br>http://www.msi.com.tw |                         | Last Revision Date:<br>Tuesday, September 03, 2002 |
| Sheet                                                                                                         | 15                      | of 29                                              |

# AGP 1.5V 2X/4X SLOT(AGP VER:2.0 COMPLY)


VCC5 = 60mils trace / 15 mils space

AGP Slot Imax  
VCC\_AGP 2.0A  
VCC3 6.0A  
VCC12 1.0A  
VCC5 2.0A  
VCC3\_SB 0.375A




INTA# INTB#

## AGP SIGNAL REFERENCE CIRCUIT




## AGP TERMINATION RESISTORS



LESS 100MILS STUB TRACE LENGTH FOR 24X  
LESS 500MIL FOR 1X MUST BE FOLLOWING  
Place these resistors between AGP slot & GMCH

## AGP SLOT DECOUPLING CAPACITORS



Micro Star Restricted Secret

|                                                                                                              |           |                                                   |
|--------------------------------------------------------------------------------------------------------------|-----------|---------------------------------------------------|
| Title                                                                                                        | AGP 2.0   | Rev                                               |
| Document Number                                                                                              | MS-6539N1 | 1.0c                                              |
| MICRO-STAR INT'L CO.,LTD.<br>No. 69 Li-De St, Jung-He City,<br>Taipei Hsien, Taiwan<br>http://www.msi.com.tw |           | Last Revision Date:<br>Monday, September 16, 2002 |
| Sheet                                                                                                        | 16        | of 29                                             |

The diagram illustrates the PCB layout for a system centered around the PCH1 microcontroller. Key components and their connections include:

- Microcontroller (PCH1):** Pins B1 through B99 are shown, connected to various signals and power rails.
- Power Supply:** The board features multiple voltage rails: +12V, -12V, +5V, +3.3V, and GND. These are distributed across the board via traces and decoupling capacitors (e.g., C254).
- Memory Chips:** AD92 (9, 24 pins) and AD18 (9, 24 pins) are connected to the microcontroller's address and data buses.
- Logic Devices:** CBE#0, CBE#1, and ACK#64 are connected to specific microcontroller pins.
- Other Components:** Various resistors (R321, R320, R323) and capacitors (C254) are used for signal conditioning and timing.
- Connectors:** The diagram shows connections to external systems, including AC\_RST#, AC\_SYNC, CNR\_AC\_BCLK, and AC\_SDINO.

```

IDSEL = AD17
MASTER = PREQ1
INTB#

```

**Pin Header 1 (Left):**

| Pin  | Signal | Value |
|------|--------|-------|
| 9,16 | INTB#  | 1     |
| 9    | PREQ#0 | 3     |
| 9,24 | PREQ#2 | 5     |
| 9    | PREQ#1 | 7     |
| 9    | PREQ#3 | R237  |

**Pin Header 2 (Right):**

| Pin  | Signal | Value |
|------|--------|-------|
| 9,24 | INTC#  | 1     |
| 9,16 | INTA#  | 3     |
| 9    | INT#   | 5     |
| 10   | INTE#  | 7     |

**Pin Header 3 (Bottom Left):**

| Pin | Signal  | Value |
|-----|---------|-------|
| 1   | DEVSEL# | 2     |
| 3   | IDY#    | 4     |
| 5   | RDY#    | 6     |
| 7   | FRAME#  | 8     |
| 8   | SEN#    | 1     |
| 9   | PERR#   | 3     |
| 10  | PLCK#   | 5     |
| 11  | STOP#   | 7     |

**Pin Header 4 (Bottom Right):**

| Pin | Signal | Value |
|-----|--------|-------|
| 10  | INTF#  | 1     |
| 9   | PREQ#4 | 3     |
| 10  | INTG#  | 5     |
| 10  | INTH#  | 7     |

**Pin Header 5 (Bottom):**

| Pin | Signal | Value |
|-----|--------|-------|
| 1   | REQ#54 | 2     |
| 3   | ACK#64 | 4     |
| 5   | R319   | 6     |
| 7   | R320   | 8     |

**Power Connections:**

- VCC5 (Pin 1)
- VCC3 (Pin 2)
- VCC4 (Pin 3)
- VCC5 (Pin 4)
- VCC5 (Pin 5)
- VCC5 (Pin 6)
- VCC5 (Pin 7)
- VCC5 (Pin 8)
- VCC5 (Pin 9)
- VCC5 (Pin 10)
- VCC5 (Pin 11)
- VCC5 (Pin 12)
- VCC5 (Pin 13)
- VCC5 (Pin 14)
- VCC5 (Pin 15)
- VCC5 (Pin 16)
- VCC5 (Pin 17)
- VCC5 (Pin 18)
- VCC5 (Pin 19)
- VCC5 (Pin 20)
- VCC5 (Pin 21)
- VCC5 (Pin 22)
- VCC5 (Pin 23)
- VCC5 (Pin 24)
- VCC5 (Pin 25)
- VCC5 (Pin 26)
- VCC5 (Pin 27)
- VCC5 (Pin 28)
- VCC5 (Pin 29)
- VCC5 (Pin 30)
- VCC5 (Pin 31)
- VCC5 (Pin 32)
- VCC5 (Pin 33)
- VCC5 (Pin 34)
- VCC5 (Pin 35)
- VCC5 (Pin 36)
- VCC5 (Pin 37)
- VCC5 (Pin 38)
- VCC5 (Pin 39)
- VCC5 (Pin 40)
- VCC5 (Pin 41)
- VCC5 (Pin 42)
- VCC5 (Pin 43)
- VCC5 (Pin 44)
- VCC5 (Pin 45)
- VCC5 (Pin 46)
- VCC5 (Pin 47)
- VCC5 (Pin 48)
- VCC5 (Pin 49)
- VCC5 (Pin 50)
- VCC5 (Pin 51)
- VCC5 (Pin 52)
- VCC5 (Pin 53)
- VCC5 (Pin 54)
- VCC5 (Pin 55)
- VCC5 (Pin 56)
- VCC5 (Pin 57)
- VCC5 (Pin 58)
- VCC5 (Pin 59)
- VCC5 (Pin 60)
- VCC5 (Pin 61)
- VCC5 (Pin 62)
- VCC5 (Pin 63)
- VCC5 (Pin 64)
- VCC5 (Pin 65)
- VCC5 (Pin 66)
- VCC5 (Pin 67)
- VCC5 (Pin 68)
- VCC5 (Pin 69)
- VCC5 (Pin 70)
- VCC5 (Pin 71)
- VCC5 (Pin 72)
- VCC5 (Pin 73)
- VCC5 (Pin 74)
- VCC5 (Pin 75)
- VCC5 (Pin 76)
- VCC5 (Pin 77)
- VCC5 (Pin 78)
- VCC5 (Pin 79)
- VCC5 (Pin 80)
- VCC5 (Pin 81)
- VCC5 (Pin 82)
- VCC5 (Pin 83)
- VCC5 (Pin 84)
- VCC5 (Pin 85)
- VCC5 (Pin 86)
- VCC5 (Pin 87)
- VCC5 (Pin 88)
- VCC5 (Pin 89)
- VCC5 (Pin 90)
- VCC5 (Pin 91)
- VCC5 (Pin 92)
- VCC5 (Pin 93)
- VCC5 (Pin 94)
- VCC5 (Pin 95)
- VCC5 (Pin 96)
- VCC5 (Pin 97)
- VCC5 (Pin 98)
- VCC5 (Pin 99)
- VCC5 (Pin 100)

**PCI SLOT DECOUPLING CAPACITORS**

VCC5

VCC3

CB134 0.1u

CB154 0.1u

CB132 0.1u

CB129 0.1u

CB128 0.1u

CB153 0.1u

CB133 0.1u

CB135 0.1u

CB155 0.1u

CB131 100p

CB127 100p

CB151 100p

CB150 100p

-12V

C178 X 0.1u

+12V

CB583 0.1u

CB126 0.1u







VCC3\_SB

CB130 0.1u


**Micro Star Restricted Secret**

|                                                              |                                                    |     |
|--------------------------------------------------------------|----------------------------------------------------|-----|
| Title                                                        | PCI SLOT 1                                         | Rev |
| Document Number                                              | MS-6539N1                                          | 1   |
| MICRO-STAR INT'L CO.,LTD.<br>No. 69, Li-De St, Jung-He City, | Last Revision Date:<br>Tuesday, September 03, 2002 |     |


|                                                                                                               |  |                                                    |       |
|---------------------------------------------------------------------------------------------------------------|--|----------------------------------------------------|-------|
| Title                                                                                                         |  | PCI SLOT 1                                         | Rev   |
| Document Number                                                                                               |  | MS-6539N1                                          | 10c   |
| MICRO-STAR INT'L CO.,LTD.<br>No. 69, Li-De St, Jung-Ho City,<br>Taipei Hsien, Taiwan<br>http://www.msi.com.tw |  | Last Revision Date:<br>Tuesday, September 03, 2002 |       |
| Sheet                                                                                                         |  | 17                                                 | of 29 |




### POWER CIRCUIT FOR USB PORT 2,3



### REAR PANEL USB CONNECTOR FOR USB PORT 2,3




### POWER CIRCUIT FOR USB PORT 0,1



- \* USB Trace width : 7.5 mils
- \* USB Trace Spacing : Low speed 20 mils, High speed 50 mils
- \* Differential USB Signlas Trace, Spacing : 7.5 mils
- \* USB Power Trace must be 40mils width
- \* Length(longest)-Length(shortest)<150mils
- \* Maxium trace length <5"


### FRONT PANEL USB CONNECTOR FOR USB PORT 0,1






**Micro Star Restricted Secret**

|                                                                                                                     |                |                            |
|---------------------------------------------------------------------------------------------------------------------|----------------|----------------------------|
| Title                                                                                                               | USB Connectors | Rev                        |
| Document Number                                                                                                     | MS-6539N1      | 1.0c                       |
| MICRO-STAR INT'L CO., LTD.                                                                                          |                | Last Revision Date:        |
| No. 69 Li-De St, Jung-He City,<br>Taipei Hsien, Taiwan<br><a href="http://www.msi.com.tw">http://www.msi.com.tw</a> |                | Monday, September 16, 2002 |
| Sheet                                                                                                               | 19             | of 29                      |



## ATX CONNECTOR



## REGULATORS OUTPUT DECOUPLING CAPACITORS



## POWER BUTTON




~~Micro Star Restricted Secret~~


|                                                                                                                      |           |                             |
|----------------------------------------------------------------------------------------------------------------------|-----------|-----------------------------|
| Title                                                                                                                |           | Rev                         |
| Front Panel,Power Conn. & Speaker                                                                                    |           |                             |
| Document Number                                                                                                      | MS-6539N1 | 1.0c                        |
| MICRO-STAR INT'L CO.,LTD.                                                                                            |           | Last Revision Date          |
| No. 69, Li-De St, Jung-Hs City,<br>Taipei Hsien, Taiwan<br><a href="http://www.msi.com.tw">http://www.msi.com.tw</a> |           | Tuesday, September 03, 2002 |
| Sheet                                                                                                                | 20        | of 29                       |




## Firware Hub (FWH)




## FWH RESISTORS



## PCB OTHER COMPONENT




## FWH DECOUPLING CAPACITORS




## SIMULATION TRACE



## FWH INIT Signal Voltage Translation Block



## AGP3.3V




$$VCC\_AGP = 1.25 \times (1 + R1232 / R1233)$$


$$3.36V = 1.25 \times (1 + 2.1K / 1.24K)$$

## GMCH 1.5V POWER TRANSLATOR

For internal AGP, Hun Link interface




## FWH write protect



## Micro Star Restricted Secret


|                                                     |           |                            |
|-----------------------------------------------------|-----------|----------------------------|
| Title                                               | FWH       | Rev                        |
| Document Number                                     | MS-6539N1 | 1.0c                       |
| MICRO-STAR INT'L CO., LTD.                          |           | Last Revision Date:        |
| No. 69 Li-De St, Jung-He City, Taipei Hsien, Taiwan |           | Monday, September 16, 2002 |
| Sheet                                               | 21 of 29  |                            |



HIP6301 -- VRM 9.0/9.2


| VID4 | VID3 | VID2 | VID1 | V | D0    | VDC(V) |
|------|------|------|------|---|-------|--------|
| 1    | 1    | 1    | 1    | 1 | OFF   |        |
| 1    | 1    | 1    | 1    | 0 | 1.100 |        |
| 1    | 1    | 1    | 0    | 1 | 1.125 |        |
| 1    | 1    | 1    | 0    | 0 | 1.150 |        |
| 1    | 1    | 0    | 1    | 1 | 1.175 |        |
| 1    | 1    | 0    | 1    | 0 | 1.200 |        |
| 1    | 1    | 0    | 0    | 1 | 1.225 |        |
| 1    | 1    | 0    | 0    | 0 | 1.250 |        |
| 1    | 0    | 1    | 1    | 1 | 1.275 |        |
| 1    | 0    | 1    | 1    | 0 | 1.300 |        |
| 1    | 0    | 1    | 0    | 1 | 1.325 |        |
| 1    | 0    | 1    | 0    | 0 | 1.350 |        |
| 1    | 0    | 0    | 1    | 1 | 1.375 |        |
| 1    | 0    | 0    | 1    | 0 | 1.400 |        |
| 1    | 0    | 0    | 0    | 1 | 1.425 |        |
| 1    | 0    | 0    | 0    | 0 | 1.450 |        |
| 0    | 1    | 1    | 1    | 1 | 1.475 |        |
| 0    | 1    | 1    | 1    | 0 | 1.500 |        |
| 0    | 1    | 1    | 0    | 1 | 1.525 |        |
| 0    | 1    | 1    | 0    | 0 | 1.550 |        |
| 0    | 1    | 0    | 1    | 1 | 1.575 |        |
| 0    | 1    | 0    | 1    | 0 | 1.600 |        |
| 0    | 1    | 0    | 0    | 1 | 1.625 |        |
| 0    | 1    | 0    | 0    | 0 | 1.650 |        |
| 0    | 0    | 1    | 1    | 1 | 1.675 |        |
| 0    | 0    | 1    | 1    | 0 | 1.700 |        |
| 0    | 0    | 1    | 0    | 1 | 1.725 |        |
| 0    | 0    | 1    | 0    | 0 | 1.750 |        |
| 0    | 0    | 0    | 1    | 1 | 1.775 |        |
| 0    | 0    | 0    | 1    | 0 | 1.800 |        |

#### VID PULL-UP RESISTORS









CHECK THIS

#### PWM GOOD




#### Micro Star Restricted Secret

|                                                      |                                                 |      |
|------------------------------------------------------|-------------------------------------------------|------|
| Title                                                | VRM 9.0                                         | Rev  |
| Document Number                                      | MS-6539N1                                       | 1.0c |
| MICRO-STAR INT'L CO., LTD.                           | Last Revision Date: Tuesday, September 03, 2002 |      |
| No. 69, Li-De St, Jung-He City, Taipei Hsien, Taiwan | Sheet 22 of 29                                  |      |
| http://www.msi.com.tw                                |                                                 |      |




**Micro Star Restricted Secret**

|                                                      |                            |                            |
|------------------------------------------------------|----------------------------|----------------------------|
| Title                                                | SMBUS Isolation & FAN Con. | Rev                        |
| Document Number                                      | MS-6539N1                  | 1.0c                       |
| MICRO-STAR INT'L CO.,LTD.                            |                            | Last Revision Date:        |
| No. 69, Li-De St, Jung-He City, Taipei Hsien, Taiwan |                            | Monday, September 16, 2002 |
| http://www.msi.com.tw                                |                            | Sheet                      |
|                                                      |                            | 23 of 29                   |






# Video Connector








PCB1



PCB,MB,6539,10c,4

P01-653910A-T39



L2\_YJUMPER-MG BIOS\_WP(1)  
YJUMPER-MG CLR\_CMOS1(2-3)  
YJUMPER-MG J3(1-2)



Pin Header Key Protect


JFP1 Pin 6  
COM1 Pin 10  
COM2 Pin 10

Micro Star Restricted Secret

|                                                                                                                                                    |                                                      |      |
|----------------------------------------------------------------------------------------------------------------------------------------------------|------------------------------------------------------|------|
| Title                                                                                                                                              | Manual Parts                                         | Rev  |
| Document Number                                                                                                                                    | MS-6539N1                                            | 1.0c |
| MICRO-STAR INT'L CO., LTD.<br>No. 69, Li-De St, Jung-He City,<br>Taipei Hsien, Taiwan<br><a href="http://www.msi.com.tw">http://www.msi.com.tw</a> | Last Revision Date:<br>Wednesday, September 04, 2002 |      |
| Sheet                                                                                                                                              | 27 of 29                                             |      |

| ATX P/S<br>with 1A Stby current |             |               |              |                |
|---------------------------------|-------------|---------------|--------------|----------------|
| 5VSB<br>+/-5%                   | 5V<br>+/-5% | 3.3V<br>+/-5% | 12V<br>+/-5% | -12V<br>+/-10% |

## Power Delivery Map



Micro Star Restricted Secret

|                                                                                                                                                   |              |                                                    |
|---------------------------------------------------------------------------------------------------------------------------------------------------|--------------|----------------------------------------------------|
| Title                                                                                                                                             | Manual Parts | Rev                                                |
| Document Number                                                                                                                                   | MS-6539N1    | 1.0c                                               |
| MICRO-STAR INT'L CO., LTD.<br>No. 69 Li-De St, Jung-He City,<br>Taipei Hsien, Taiwan<br><a href="http://www.msi.com.tw">http://www.msi.com.tw</a> |              | Last Revision Date:<br>Tuesday, September 03, 2002 |
| Sheet                                                                                                                                             | 28           | of 29                                              |

FWH

| GPIO Pin | Type | Function                             |
|----------|------|--------------------------------------|
| GPI 0    | I    | Pull down through 8.2K ohms (unused) |
| GPI 1    | I    | Pull down through 8.2K ohms (unused) |
| GPI 2    | I    | P1 customer defined                  |
| GPI 3    | I    | P1 customer defined                  |
| GPI 4    | I    | Pull down through 8.2K ohms (unused) |

PCI Config.

| DEVICE             | ICH INT Pin                      | IDSEL | CLOCK   | CLK GEN PIN OUT |
|--------------------|----------------------------------|-------|---------|-----------------|
| PCI Slot 1         | INTA#<br>INTB#<br>INTC#<br>INTD# | AD16  | PCICLK0 | PIN 12          |
| PCI Slot 2         | INTB#<br>INTC#<br>INTD#<br>INTA# | AD17  | PCICLK1 | PIN 14          |
| PCI LAN<br>82540EM | INTC#<br>INTD#<br>INTA#<br>INTB# | AD18  | LAN_CLK | PIN 11          |

\*ICH4 reserved PCI address line AD22 for the PCI-to-ISA Bridge's IDSEL input.

DIMM Config.

| DEVICE | ADDRESS  | CLOCK                                        |
|--------|----------|----------------------------------------------|
| DIMM 1 | 1010000B | DCLK0/DCLK0#<br>DCLK1/DCLK1#<br>DCLK2/DCLK2# |
| DIMM 2 | 1010001B | DCLK3/DCLK3#<br>DCLK4/DCLK4#<br>DCLK5/DCLK5# |

General SPEC

ICH4

| GPIO Pin   | Type | Function                                         |
|------------|------|--------------------------------------------------|
| GPIO 0     | I    | REQ#A (multifunction pin)                        |
| GPIO 1     | I    | REQ#B (multifunction pin)                        |
| GPIO 2     | I    | Pull up through 8.2K ohms (PIRQE#)               |
| GPIO 3     | I    | Pull up through 8.2K ohms (PIRQF#)               |
| GPIO 4     | I    | Pull up through 8.2K ohms (PIRQG#)               |
| GPIO 5     | I    | Pull up through 8.2K ohms (PIRQH#)               |
| GPIO 6     | I    | Pull down through 10K ohms (unused)              |
| GPIO 7     | I    | For password Clear                               |
| GPIO 8     | I    | Pull Up to 3.3VSBY through 4.7K ohms (SIO_PME)   |
| GPIO 9     | I    | Not Implemented                                  |
| GPIO 10    | I    | Not Implemented                                  |
| GPIO 11    | I    | SMB_ALERT (multifunction pin)                    |
| GPIO 12    | I    | EXTSMI# with Pull up 10K ohms to VCC3_SB         |
| GPIO 13    | I    | Pull down through 10K ohms (unused)              |
| GPIO 14~15 | I    | Not Implemented                                  |
| GPIO 16    | O    | GNT#A (multifunction pin)                        |
| GPIO 17    | O    | GNT#B (multifunction pin)                        |
| GPIO 18*   | O    | No Connected                                     |
| GPIO 19    | O    | No Connected                                     |
| GPIO 20    | O    | No Connected                                     |
| GPIO 21    | O    | Lan disable                                      |
| GPIO 22    | OD   | No Connected                                     |
| GPIO 23    | O    | Pull Up to 3.3V through 8.2K ohms (BIOS protect) |
| GPIO 24    | I/O  | No Connected                                     |
| GPIO 25    | I/O  | No Connected                                     |
| GPIO 26    | I/O  | Not Implemented                                  |
| GPIO 27    | I/O  | No Connected                                     |
| GPIO 28    | I/O  | No Connected                                     |
| GPIO 29~31 | O    | Not Implemented                                  |
| GPIO 32    | I/O  | No Connected                                     |
| GPIO 33    | I/O  | No Connected                                     |
| GPIO 34    | I/O  | Primary IDE ATA66/100 detection (PD_DET)         |
| GPIO 35    | I/O  | Secondary IDE ATA66/100 detection (SD_DET)       |
| GPIO 36    | I/O  | No Connected                                     |
| GPIO 37    | I/O  | No Connected                                     |
| GPIO 38    | I/O  | No Connected                                     |
| GPIO 39    | I/O  | No Connected                                     |
| GPIO 40    | I/O  | No Connected                                     |
| GPIO 41    | I/O  | No Connected                                     |
| GPIO 42    | I/O  | No Connected                                     |
| GPIO 43    | I/O  | No Connected                                     |
| GPIO 44~47 | I/O  | Not Implemented                                  |

\* GPIO18 will toggle at 1Hz frequency.

| DATE       | Rev          | Description                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
|------------|--------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 2002/ 5/18 | 0A           | The initial version.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        |
| 2002/ 6/10 | 0B           | P.03 To exchange the reference name with IDE1 and IDE2.<br>P.03 Add R486 for PCI_LAN clock.<br>P.09 Add the PREQ/PREQT2 for PCI_LAN.<br>P.09 Deleted the 82562ET circuit.<br>P.10 Add the R485 for ICH4-GPIO11 pull-up(SMBALERT#).<br>P.13 Modify headphone-out circuit(R280,R199).<br>P.13 Modify U11 circuit capcitor from 47uF(EC6) to 100uF(CT33).<br>P.19 Deleted the c122.<br>P.18 Deleted the WOM connector circuit for space saving.<br>P.18 Deleted the Wake On LAN Header circuit for space saving.<br>P.18 Deleted the CT7 and CT8.<br>P.18 To exchange the reference name with COM1 and COM2.<br>P.23 Modify CPU Fan circuit capcitor from 22uF(EC20) to 100uF(CT33).<br>P.24 Modify LAN solution from 82562ET to 82540EM(NEC requirement).<br>P.25 Modify the MEM_STR circuit. |
| 2002/ 6/11 | 0B           | P.24 Modify LAN_V15 and LAN_V25 circuit because Total power dissipation issue .                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |
| 2002/ 6/13 | 0B           | P.23 Add the R490 and 491 for U15.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |
| 2002/ 6/17 | 0B           | P.19 Deleted the L5,L17 from USB power circuit.<br>P.27 Add the C254 for PCI-SLOT RST#(for SI).                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |
| 2002/ 6/18 | 0B           | P.03 Add the C255 for LANCLK (EMI).<br>P.24 Modify LAN LED definition(GREEN for speed; AMBER for Active/link).                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |
| 2002/ 6/20 | 0B           | P.24 The U23-pin25 connect to VCC_AGP3_3 because layout issue .                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |
| 2002/ 6/24 | 0B           | P.08 Deleted the CT23, Added the EC23 and CB243.<br>P.25 Deleted the CT30, Added the CB241 and CB242.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |
| 2002/ 6/25 | 0B           | P.19 Deleted the L4,L16 from USB power circuit.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |
| 2002/ 6/27 | 0B           | P.10 Add the R497 and 498 for S5.(To fix DDR 2.5V abnormally when the system go to S4).                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |
| 2002/ 7/25 | 1.0          | P.6 Deleted the R332(0ohm).<br>P.9 Deleted the R215(0ohm).<br>P.11 Deleted the R05(0ohm).<br>P.11 and P.23Add the RC256-259 for SMBus Signal integrityI.<br>P.18 Deleted the FB19(0ohm).<br>P.23 Modify FAN control circuit( follow AD recommend).<br>P.25 Deleted the R384(0ohm).<br>P.25 The MSS-RSMRST# circuit merge with discrete RSMRST# circuit.                                                                                                                                                                                                                                                                                                                                                                                                                                     |
| 2002/ 8/05 | 1.0          | P.24 The Delete the CT29 for EMI issue.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |
| 2002/ 8/06 | 1.0          | P.24 The Delete the CB239,240,FB18 for EMI issue.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           |
| 2002/ 8/20 | 1.0a<br>1.0a | P.13 Chassis GND and signal GND are isolated at JM1C and LINE02.<br>P.18 Deleted the CP1 and CP3.<br>P.19 Chassis GND and signal GND are isolated at USB.<br>P.21 The BStand BS2,BS3 connect to GND.(for MIC noise issue when system in chassis)<br>P.24 Add the U29 for 82540-Lan diasble function .                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |
| 2002/ 9/03 | 1.0b<br>1.0c | Add the ESD solution.<br>Add the ESD solution.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |

|                                                         |  |                             |
|---------------------------------------------------------|--|-----------------------------|
| Title                                                   |  | Rev                         |
| Manual Parts                                            |  |                             |
| Document Number                                         |  | 1.0c                        |
| MS-6539N1                                               |  |                             |
| MICRO-STAR INT'L CO.,LTD.                               |  | Last Revision Date:         |
| No. 69, Li-De St, Jung-He City,<br>Taipei Hsien, Taiwan |  | Tuesday, September 03, 2002 |
| http://www.msi.com.tw                                   |  | Sheet                       |
|                                                         |  | 29 of 29                    |