

MS-6717 V.100

CPU: AMD Socket-462 Processor
Chipset: SIS 746

SIS 963 SOUTH BRIDGE

LPC I/O: W83697HF

AC'97 CODEC:Realtek ALC650

Expansion: PCI Slot * 5

MSI Power On / Suspend LED State

BIOS	S0	S1/S3	S5
Single Color	Green	Off	Off
Dual Color	Green	Red	Off
Green: MSI_LED1=' 1' MSI_LED2=' 0' Red : MSI_LED1=' 0' MSI_LED2=' 1' Single Color S1/S3 status: MSI_LED1=' 0' MSI_LED2=' 1'			

MSI ACPILED & VDIM state

BIOS	S0	S1/S3	S5
Single Color	ACPILED:Low VDIM :Hi	ACPILED:Hi & VDIM:Hi	ACPILED:Hi-Z VDIM :Low
Dual Color	ACPILED:Low VDIM :Hi	ACPILED:Hi & VDIM:Hi	ACPILED:Hi-Z VDIM :Low
Note : 1). 1Hz means Blinking frequency of ACPILED signal. 2). VDIM is no voltage in S5 state.			

CONTENT	PAGE
Cover Page	1
Block Diagram	2
Clock Gen.& Clock Buffer	3-4
AMD Socket A	5-6
SiS 746 Host / AGP	7
SiS 746 Memory	8
746 MuTioI/Other	9
746 POWER	10
SIS 963	11-14
DDR SLOT 1-3	15-16
DDR Termination	17
AGP Slot	18
PCI slot 1~6	19-21
LAN PHY(RTL8201) & RJ45	22
IDE Connector	23
USB connector	24
KB/MS Connector	25
AC'97 CODEC	26
Audio Connector	27
LPC I/O W83697HF	28
Flash & FAN & H/wMonitor	29
Parallel Port	30
Serial Port	31
PWM ST6911D	32
ACPI Contorller	33
Front Panel&ATX power CONN.	34
SCREW MENU	35

MICRO-STAR INT'L CO.,LTD.

Title
COVER SHEET


Size Document Number
MS-6717



Custom

Date: Wednesday, November 06, 2002 Sheet 1 of 36



Rev
0B

MS-6717 Block Diagram









By-Pass Capacitors Place near to the Clock Buffer





Clock Buffer (FOR 3 DDR SDRAM DIMMS)




AMD 462PGA Socket - Signals




CPU APIC BLOCK



CPU FERR BLOCK




CPU SYSCLK BLOCK




Near socket-A

CPU SYSCLK REFERENCE BLOCK




CPU ZN / ZP BLOCK



*100:FOR S2K PMOS DRIVING


match the transmission line
Push-pull compensation circuit

CPU K7CLKOUT BLOCK




* Trace lengths of CLKOUT and -CLKOUT are between 2" and 3"

MICRO-STAR INT'L CO.,LTD.			
Title SOCKET A SIGNALS			
Size	Document Number		
Custom	MS-6717		
Date:	Monday, December 23, 2002	Sheet	5 of 36
			Rev 0B





The differences between the traces of MuTIOL Strokes and Data should be smaller than 0.05"





746-3

MuTIOL


The differences between the traces of MuTIOL Strokes and Data should be smaller than 0.05"






Place near 746 chip.







MICRO-STAR INT'L CO.,LTD.			
Title 746-3			
Size	Document Number MS-6717		Rev 0B
Custom			
Date:	Monday, December 23, 2002	Sheet 9 of 36	




















SSTL-2 Termination Resistors

RMD[0..63] << RMD[0..63] (8,15,16)
 RDQM[0..7] << RDQM[0..7] (8,15,16)
 RDQS[0..7] << RDQS[0..7] (8,15,16)
 RMA[0..14] << RMA[0..14] (8,15,16)
 RCS#[0..5] << RCS#[0..5] (8,15,16)


	SDR		DDR		
MD/DQM(/DQS)	LV-CMOS	RS	9/10/-	SSTL-2	RS
MA/Control	LV-CMOS	IO	9	SSTL-2	RTT
CS	LV-CMOS			SSTL-2	
CKE	DD 3.3V		DD 2.5V		



NOTE: This page is for universal PCB design(suitable for both 645 or 650)




Place Closed to AGP socket








CLOSED TO AGP SLOT



MICRO-STAR INT'L CO.,LTD.			
Title AGP SLOT			
Size	Document Number	Rev	
Custom	MS-6717	0B	
Date:	Tuesday, December 24, 2002	Sheet	18 of 36




PCI BUS PULL-UP




*100:ADD FOR LAN
PHY & PCI POWER




*100:ADD FOR EMI




MICRO-STAR INTL CO.,LTD.			
Title			
PCI 1 & 6			
Size	Document Number		Rev
	CustomMS-6717		0B
Date:	Monday, December 23, 2002	Sheet	19 of 36








RTL8201


*10A:PIN32 DVDD25 OUTPUT TO PIN 8 DVDD25 INPUT.












MICRO-STAR INT'L CO.,LTD.			
Title			
AC'97 CODEC			
Size			
Document Number			
MS-6717			
Custom			
Date			
Tuesday, December 24, 2002			
Sheet			
26 of 36			
Rev			
0B			





(26) LOUT_R >> LOUT_R
(26) LOUT_L >> LOUT_L











SELECT 2MB OR 4MB
2M UNSTALL
4M INSTALL







Hardware Monitor




MICRO-STAR INT'L CO.,LTD.			
Title	FLASHROM & HW MONITOR		
Size	Document Number	Rev	
Custom	MS-6717	0B	
Date:	Tuesday, December 24, 2002	Sheet	29 of 36









VID4	VID3	VID2	VID1	VID0	VDC(V)
1	0	1	1	0	1.30
1	0	0	0	1	1.425
1	0	0	0	0	1.45
0	1	1	1	1	1.475
0	1	1	1	0	1.500
0	1	1	0	1	1.525
0	1	1	0	0	1.550
0	1	0	1	1	1.575
0	1	0	1	0	1.600
0	1	0	0	1	1.625
0	0	1	1	1	1.650
0	0	1	1	0	1.675
0	0	1	0	1	1.70
0	0	1	0	0	1.725
0	0	1	0	0	1.75
0	0	0	1	1	1.775
0	0	0	1	0	1.80
0	0	0	0	1	1.825
0	0	0	0	0	1.85
1	1	1	1	1	NO CPU








MICRO-STAR INT'L CO.,LTD.			
Title	PWM (VRM 9.0)		
Size	Document Number	Rev	
Custom	MS-6717	OB	
Date:	Monday, December 23, 2002	Sheet	32 of 36





INTEL / MSI CONN



For EMI



High Freq. return current decoupling



MICRO-STAR INT'L CO.,LTD.				
Title				
SREW / MENU				
Size Custom	Document Number MS-6717			Rev 0B
Date:	Tuesday, December 24, 2002	Sheet	35 of 36	

11/11	V.100
PAGE3	*.R147,148 CHANGE VALUE 10 OHM TO 33. *.C198,199 -->15P *.ADD R4 10K
PAGE4	*.C151-->NO STUFF
PAGE5	*.R19 CHANGE VALUE 40.2 OHM TO 56.2 OHM
PAGE6	*.C102-->NO STUFF
PAGE9	*.C265,C263CHANGE VALUE-->0.1U
PAGE12	*.C343-->NO STUFF *.C328,C344 20P-->15P *.R224,R225,R238,R239,R240,R243 330HM-->00HM
PAGE13	*.R10-->NO STUFF *.U6 PIN2 ADD R364 NO STUFF
PAGE22	*.R175 CHANGE VALUE 2K TO 5.9K *.ADD C484,C485 10UF FOR 3VSBY *.C213 0.1UF-->100P *.R190,R202 22ohm-->0ohm *.RN73,RN74,RN75,R194 1K-->5.1K *.C253,D17,R177,C213 NO STUFF *.C278,C280 10P-->20P
PAGE25	*.RN1 10K-->4.7K
PAGE26	*.SPEAK FUNCTION REMOVE,C380,C381,R328,R319,R343,Q36,RN98,Q33,R237-->NO STUFF *.C367-->NO STUFF *.C378,C379-->0.1U
PAGE32	*.ADD 4.7UF*4 IN VCORE PLAN C476-C479 *.R32,R33 CAHNGE VALUE-->33 OHM
PAGE33	*.ADD 4.7UF C480 IN VCC3 PLAN CLOSE TO Q28 *.D14-->NO STUFF *.R101-->2.2K *.CHANGE MOS Q26 NDS351AN-S-SOT23-->PD3055LD *.ADD C481 4.7UF
PAGE34	*.ADD EC42,43 1000UF*2 IN VCC3 PLAN CLOSE TO AGP SLOT *.R5 4.7K-->10K , C9 102P-->0.1U
PAGE19	*.ADD EC25 FOR EMI
PAGE29	*.ADD EC33 FOR EMI
	V.10A
PAGE3	*.R149,150 CHANGE VALUE 22 OHM TO 33. *.C204,205 -->15P
PAGE18	*.ADD C475 0.1U to 1U *.ADD C488-->4.7U,C489--> 0.01U
PAGE22	*.U9 PIN32 2.5V OUT CONNECT TO PIN8
PAGE26	*.ADD R366, R367, R368 TO FIXED CD ROM NOISE. *.R322, R323, R324 4.7K-->47K *.FIX Mic_IN NOISE ISSUE.
PAGE33	*.ADD R365 1K PULL UP (S3AUX# 0D) *.C190 472P STUFF
PAGE13	*.RN78,RN79,R223,R266 NO STUFF
	*.Audio codec Realtek change version to F *.SIO change version *.NB change version 746-->A2 , SB-->963L C1 *.AGP 3.0 slot -->red color *.DDR slot -->green color *.TXT print -->746F Ultra *.Solder side CAP no stuff

Title		
{Title}		
Size	Document Number	
B	{Doc}	
Date:		Rev
Tuesday, December 17, 2002		(RevCode)
Sheet		
1		
36		
of		
36		