

Cover Sheet	1
Block Diagram	2
GPIO	3
Intel mPGA478B CPU - Signals	4
Intel mPGA478B CPU - Power	5
Intel Breeds Hill - Host Signals	6
Intel Breeds Hill - Memory Signals	7
Intel Breeds Hill - AGP	8
DDR DIMM 1,2	9
PCB Holes	10
ICH5(1)	11
ICH5(2)	12
ICS952611 & FWH & FDD	13
LPC I/O -W83627THF	14
AC97 Audio	15
AGP 4X/8X Slot & FAN	16
PCI Slots 1 & 2 & 3	17
PCI Slots 4 & 5	18
ATA33/66/100 IDE & Video Connectors	19
USB Connectors	20
ACPI controller	21
ATX & Front Panel	22
VRM 10.0 FMB2	23
DLED BRACKET	24
VID Adjust	25
EMI parts	26
RTL8100C/8110S	27
LAN Connector	28

MS(6788)

Version 200

Intel (R) Breeds Hill (GMCH) + ICH5 Chipset
Intel Northwood mPGA478B Processor

CPU:

Intel Northwood

System Chipset:

Intel Breeds Hill - GMCH (North Bridge)
Intel ICH5 (South Bridge)

On Board Chipset:

BIOS -- FWH EEPROM
AC'97 Codec -- ALC655
LPC Super I/O -- W83627THF
LAN --RTL8100C/8110S
CLOCK --ICS 952611

Main Memory:

DDR * 3 (Max 3GB)

Expansion Slots:

PCI2.3 SLOT * 5

ST PWM:

Controller: ST L6710



ICH5

GPIO Pin	Type	Function	Power well
GPIO 0	I	PREQ#B	MAIN
GPIO 1	I	PREQ#B	MAIN
GPIO 2	I	PIRQ#E	MAIN
GPIO 3	I	PIRQ#F	MAIN
GPIO 4	I	PIRQ#G	MAIN
GPIO 5	I	PIRQ#H	MAIN
GPIO 6	I	GPI6	MAIN
GPIO 7	I	GPI7	MAIN
GPIO 8	I	CSA_PME#	RESUME
GPIO 9	I	OC4#	RESUME
GPIO 10	I	OC5#	RESUME
GPIO 11	I	SIO_SMI#	RESUME
GPIO 12	I	EXTSMI#	RESUME
GPIO 13	I	SIO_PME#	RESUME
GPIO 14	I	OC#6	RESUME
GPIO 15	I	OC#7	RESUME
GPIO 16	O	PGNT#A	MAIN
GPIO 17	O	PGNT#B	MAIN
GPIO 18	O	GPO18	MAIN
GPIO 19	O	BIOS_WP#	MAIN
GPIO 20	O	GPO20	MAIN
GPIO 21	O	GPO21	MAIN
GPIO 22	OD	GPO22	MAIN
GPIO 23	O	GPO23	MAIN
GPIO 24	I/O	GPIO24	RESUME
GPIO 25	I/O	LAN_DISABLE#	RESUME
GPIO 27	I/O	GPIO27	RESUME
* GPIO 28	I/O	GPIO28	RESUME
GPIO 32	I/O	GPIO32	MAIN
GPIO 33	I/O	GPIO33	MAIN
GPIO 34	I/O	GPIO34	MAIN
GPIO 40	I	PREQ#4	MAIN
GPIO 41	I	GPI41	MAIN
GPIO 48	O	PGNT#4	MAIN
GPIO 49	OD	CPUPWRGD	MAIN

default output
default output
default output
default output
default output
default output

FWH

GPIO Pin	Type	Function
GPI 0	I	PD_DET
GPI 1	I	SD_DET
* GPI 2	I	Pull down through 1K ohms (unused)
GPI 3	I	Pull down through 1K ohms (unused)
* GPI 4	I	Pull down through 1K ohms (unused)

PCI Config.

DEVICE	MCP1 INT Pin	REQ# / GNT#	IDSEL	CLOCK	CLK GEN PIN OUT
PCI Slot 1	INTA# INTB# INTC# INTD#	PCI_REQ#0 PCI_GNT#0	AD16	PCICLK0	13 (PCI_CLK0)
PCI Slot 2	INTB# INTC# INTD# INTA#	PCI_REQ#1 PCI_GNT#1	AD17	PCICLK1	14 (PCI_CLK1)
PCI Slot 3	INTC# INTD# INTA# INTB#	PCI_REQ#2 PCI_GNT#2	AD18	PCICLK2	15 (PCI_CLK2)
PCI Slot 4	INTD# INTA# INTB# INTC#	PCI_REQ#3 PCI_GNT#3	AD19	PCICLK3	16 (PCI_CLK3)
PCI Slot 5	INTB# INTC# INTD# INTA#	PCI_REQ#4 PCI_GNT#4	AD21	PCICLK4	19 (PCI_CLK4)


DDR DIMM Config.

DEVICE	ADDRESS	CLOCK
DIMM 1	1010000B	MCLK_A0/MCLK_A0# MCLK_A1/MCLK_A1# MCLK_A2/MCLK_A2#
DIMM 2	1010001B	MCLK_B0/MCLK_B0# MCLK_B1/MCLK_B1# MCLK_B2/MCLK_B2#

PCI RESET DEVICE

Signals	Target
PCIRST#1	Springdale, LAN, FWH, Super I/O
PCIRST#2	PCI slot 1-3, AGP slot
HD_RST#	Primary, Scndary IDE

CPU SIGNAL BLOCK




VIDPWRGD DC Specifications



	Min	Typ	Max
VIL			0.3
VIH	0.9		

It must route to the enable pin of PWM and CK-409.
VIDGD to Vccp delay time is from 1ms to 10ms.
VIDGD rising time is 150ns.

CPU GTL REFERENCE VOLTAGE BLOCK



CPU ITP BLOCK



CPU STRAPPING RESISTORS




ALL COMPONENTS CLOSE TO CPU



MICRO-STAR INT'L CO., LTD.

Title			
Intel mPGA478B - Signals			
Size	Document Number	Rev	
	MS-6788	10A	
Date	Wednesday, September 22, 2004	Sheet	4 of 29



DDR DIMM1

SIGNALS

POWER

ADDR=1010000B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

DDR DIMM2

SIGNALS

POWER

ADDR=1010000B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

ADDR=1010001B

DDR Termination Resistors

DDR Termination Resistors

MICRO-STAR INT'L CO., LTD.

DDR DIMM 1 & 2


MS-6788

Rev 10A


Date: Wednesday, September 22, 2004

Sheet 9 of 29


Optics Orientation Holes




Mounting Holes






Simulation



DDR DIMM3







LPC SUPER I/O W83627HF/NHF/THF

SERIAL PORT 1

PARALLEL PORT

PS2 KEYBOARD & MOUSE CONNECTOR

W83627HF

VTIN GND

LPC I/O STRAPPING RESISTOR

VCC5 ○ R208 4.7KR SOUTA

VCC5 ○ R239 4.7KR SOUTB

R84 4.7KR

R210 4.7KR RTSA#

R209 4.7KR DTRA#

SOUTA	L: Disable KBC	H: Enable KBC
SOUTB	L: 24MHz	H: 48MHz
RTSA#	L: CFAD=2E	H: CFAD=4E
DTRA#	L: PNP Default	H: PNP no Default

Chassis Intrusion

VBAT0

R237 2MR

CHASSIS

JC11

1

2

X_H1X2_black

VCC5

R860 10KR

REEP

R861 4.7KR

Q85 N-MMBT3904_SOT23

ALARM

22

VTIN_GND

FB9

CP13

X OR

VTIN_GND

4

TMP_VREF

R263 10KR1%

SYS_TMP

RT2 10KR11%/0805

VTIN_GND

NOTE: LOCATE CLOSE STATUS PANEL

MICRO-STAR INT'L CO., LTD.

LPC SUPER I/O & CONNECTORS

Size Document Number Rev 10A


MS-6788

Date: Wednesday, September 22, 2004 Sheet 14 of 29

AC'97 Codec -- C-medin9739A/ALC650


AUDIO CODE REGULATORS

COPPER









FRONT AUDIO

SPEAKER OUT



LINE IN

MIC IN




AGP 1.5V 4X/8X SLOT(AGP VER:3.0)

VCC5 = 60mils trace / 15 mils space


AGP Slot Imax

VCCq 2.0A
VCC3 6.0A
VCC12 1.0A
VCC5 2.0A
VCC3_SB 0.75A




PIRQ#A / PIRQ#B


CPU FAN



SYSTEM FAN




Springdale Reference & Swing Voltage Circuit




AGP TERMINATION RESISTORS




AGP SLOT DECOUPLING CAPACITORS



MICRO-STAR INT'L CO., LTD.		
Title AGP 1.5V SLOT & FAN		
Size	Document Number MS-6788	Rev 10A
Date	Friday, June 04, 2004	Sheet 16 of 29




```
IDSEL = AD19
MASTER = PREQ#3
PIRQ#D
```



```

IDSEL = AD21
MASTER = PREQ#4
PIRQ#B

```





```
IDSEL = AD20
MASTER =PREQ#A
PIRQ#A
```


PRIMARY IDE BLOCK

ATA 33/66/100 IDE Connectors





SECONDARY IDE BLOCK




POWER CIRCUIT FOR USB PORT 4,5,6,7




REAR PANEL USB CONNECTOR FOR USB PORT 4,5,6,7




POWER CIRCUIT FOR USB PORT 2,3




REAR PANEL USB CONNECTOR FOR USB PORT 2,3




POWER CIRCUIT FOR USB PORT 0,1



REAR PANEL USB CONNECTOR FOR USB PORT 0,1



ACPI Controller




MICRO-STAR INT'L CO., LTD.

Title	MS7 ACPI controller
-------	---------------------


Size	Document Number
	MS-6788

Date: Wednesday, September 22, 2004 Sheet 21 of 29


ATX Connector




IR Connector




SATA CONNECTOR




INTEL/PB Front Panel Connector



MSI Front Panel Connector




Intel reference GMCH VTT power circuit




BOOT	CPU	Voltage
LOW	Northwood	1.45V
HIGH	Prescott	1.225V




MICRO-STAR INT'L CO., LTD.

Title ATX Connector & Front Panel		
Size	Document Number MS-6788	Rev 10A
Date	Wednesday, September 22, 2004	Sheet 22 of 29





MICRO-STAR INT'L CO., LTD.		
Title VID Adjust		
Size	Document Number MS-6788	Rev 10A
Date: Wednesday, September 22, 2004	Sheet 25 of 29	



MICRO-STAR INT'L CO., LTD.

Title

EMI PART

Size

Document Number

MS-6788

Rev

10A

Date:


Thursday, January 08, 2004


Sheet

26

of

29






Jumper Setting & Connector Setting

The diagram illustrates the jumper and connector settings for a motherboard. Key components and their settings are as follows:

- Connectors:**
 - LPT_B:** A 25-pin connector with pins 26, 27, 28, 29, and 30 labeled.
 - CONN-COM:** A connector with pins 31, 32, 33, and 34 labeled.
 - BIOS1_X:** A connector with pins 1, 2, 3, 4, 5, 6, 7, 8, 9, 10, 11, 12, 13, 14, 15, 16, 17, 18, 19, 20, 21, 22, 23, 24, 25, 26, 27, 28, 29, 30, 31, 32, 33, 34, 35, 36, 37, 38, 39, 40, 41, 42, 43, 44, 45, 46, 47, 48, 49, 50, 51, 52, 53, 54, 55, 56, 57, 58, 59, 60, 61, 62, 63, 64, 65, 66, 67, 68, 69, 70, 71, 72, 73, 74, 75, 76, 77, 78, 79, 80, 81, 82, 83, 84, 85, 86, 87, 88, 89, 90, 91, 92, 93, 94, 95, 96, 97, 98, 99, 100, 101, 102, 103, 104, 105, 106, 107, 108, 109, 110, 111, 112, 113, 114, 115, 116, 117, 118, 119, 120, 121, 122, 123, 124, 125, 126, 127, 128, 129, 130, 131, 132, 133, 134, 135, 136, 137, 138, 139, 140, 141, 142, 143, 144, 145, 146, 147, 148, 149, 150, 151, 152, 153, 154, 155, 156, 157, 158, 159, 160, 161, 162, 163, 164, 165, 166, 167, 168, 169, 170, 171, 172, 173, 174, 175, 176, 177, 178, 179, 180, 181, 182, 183, 184, 185, 186, 187, 188, 189, 190, 191, 192, 193, 194, 195, 196, 197, 198, 199, 200, 201, 202, 203, 204, 205, 206, 207, 208, 209, 210, 211, 212, 213, 214, 215, 216, 217, 218, 219, 220, 221, 222, 223, 224, 225, 226, 227, 228, 229, 230, 231, 232, 233, 234, 235, 236, 237, 238, 239, 240, 241, 242, 243, 244, 245, 246, 247, 248, 249, 250, 251, 252, 253, 254, 255, 256, 257, 258, 259, 260, 261, 262, 263, 264, 265, 266, 267, 268, 269, 270, 271, 272, 273, 274, 275, 276, 277, 278, 279, 280, 281, 282, 283, 284, 285, 286, 287, 288, 289, 290, 291, 292, 293, 294, 295, 296, 297, 298, 299, 300, 301, 302, 303, 304, 305, 306, 307, 308, 309, 310, 311, 312, 313, 314, 315, 316, 317, 318, 319, 320, 321, 322, 323, 324, 325, 326, 327, 328, 329, 330, 331, 332, 333, 334, 335, 336, 337, 338, 339, 340, 341, 342, 343, 344, 345, 346, 347, 348, 349, 350, 351, 352, 353, 354, 355, 356, 357, 358, 359, 360, 361, 362, 363, 364, 365, 366, 367, 368, 369, 370, 371, 372, 373, 374, 375, 376, 377, 378, 379, 380, 381, 382, 383, 384, 385, 386, 387, 388, 389, 390, 391, 392, 393, 394, 395, 396, 397, 398, 399, 400, 401, 402, 403, 404, 405, 406, 407, 408, 409, 410, 411, 412, 413, 414, 415, 416, 417, 418, 419, 420, 421, 422, 423, 424, 425, 426, 427, 428, 429, 430, 431, 432, 433, 434, 435, 436, 437, 438, 439, 440, 441, 442, 443, 444, 445, 446, 447, 448, 449, 450, 451, 452, 453, 454, 455, 456, 457, 458, 459, 460, 461, 462, 463, 464, 465, 466, 467, 468, 469, 470, 471, 472, 473, 474, 475, 476, 477, 478, 479, 480, 481, 482, 483, 484, 485, 486, 487, 488, 489, 490, 491, 492, 493, 494, 495, 496, 497, 498, 499, 500, 501, 502, 503, 504, 505, 506, 507, 508, 509, 510, 511, 512, 513, 514, 515, 516, 517, 518, 519, 520, 521, 522, 523, 524, 525, 526, 527, 528, 529, 530, 531, 532, 533, 534, 535, 536, 537, 538, 539, 540, 541, 542, 543, 544, 545, 546, 547, 548, 549, 550, 551, 552, 553, 554, 555, 556, 557, 558, 559, 560, 561, 562, 563, 564, 565, 566, 567, 568, 569, 570, 571, 572, 573, 574, 575, 576, 577, 578, 579, 580, 581, 582, 583, 584, 585, 586, 587, 588, 589, 590, 591, 592, 593, 594, 595, 596, 597, 598, 599, 600, 601, 602, 603, 604, 605, 606, 607, 608, 609, 610, 611, 612, 613, 614, 615, 616, 617, 618, 619, 620, 621, 622, 623, 624, 625, 626, 627, 628, 629, 630, 631, 632, 633, 634, 635, 636, 637, 638, 639, 640, 641, 642, 643, 644, 645, 646, 647, 648, 649, 650, 651, 652, 653, 654, 655, 656, 657, 658, 659, 660, 661, 662, 663, 664, 665, 666, 667, 668, 669, 670, 671, 672, 673, 674, 675, 676, 677, 678, 679, 680, 681, 682, 683, 684, 685, 686, 687, 688, 689, 690, 691, 692, 693, 694, 695, 696, 697, 698, 699, 700, 701, 702, 703, 704, 705, 706, 707, 708, 709, 710, 711, 712, 713, 714, 715, 716, 717, 718, 719, 720, 721, 722, 723, 724, 725, 726, 727, 728, 729, 730, 731, 732, 733, 734, 735, 736, 737, 738, 739, 740, 741, 742, 743, 744, 745, 746, 747, 748, 749, 750, 751, 752, 753, 754, 755, 756, 757, 758, 759, 760, 761, 762, 763, 764, 765, 766, 767, 768, 769, 770, 771, 772, 773, 774, 775, 776, 777, 778, 779, 780,



Title	BOM PART
-------	----------

Size	Document Number	Rev
	MS-6788	10A

Date: Wednesday, September 22, 2004 Sheet 29 of 29