

8S661FXMTIU- IU Schematics

| SHEET | TITLE                                            |
|-------|--------------------------------------------------|
| 1     | COVER SHEET                                      |
| 2     | BOM & PCB MODIFY HISTORY                         |
| 3     | BLOCK DIAGRAM                                    |
| 4,5,6 | INTEL CPU_WMT_478                                |
| 7-10  | SIS661FX (NORTH BRIDGE) HOST; DDR; AGP,HYPER ZIP |
| 11-14 | SIS964L (SOUTH BIRDGE)                           |
| 15    | CLOCK GENERATOR (ICS952018AF), BUFFER(ICS93722)  |
| 16,17 | DDR SDRAM DIMMS 1,2                              |
| 18    | AGP SLOT                                         |
| 19    | PCI SLOT 1,2,3                                   |
| 20    | IDE,FRONT USB,PCIRST#                            |
| 21    | LPCIO_IT8705                                     |
| 22    | BIOS                                             |
| 23    | COM,PRT,FDD,KB/MS,IR                             |
| 24    | AC 97 ALC655                                     |
| 25    | AUDIO JACK,SPDIF                                 |
| 26    | FAN, IR                                          |
| 27    | PANEL,STR LED,FANS ,CPU GN                       |
| 28    | VCORE PWM FAN5019 + FAN5009                      |
| 29    | VDDQ,VCC18,VTT_GMCH DC POWER                     |
| 30    | ATX CONN, GPIO LIST                              |
| 31    | DDR POWER                                        |

| SHEET | TITLE               |
|-------|---------------------|
| 32    | RTL8100C 10/100 LAN |
| 33    | VGA CONNECTOR       |
|       |                     |

PCB Size: 244\*230 mm

COMPONENT SIDE  
(1 oz. Copper)  
VCC LAYER  
(1 oz. Copper)  
GND LAYER  
(1 oz. Copper)  
SOLDER SIDE  
(1 oz. Copper)

GIGABYTE

Title

COVER SHEET

Size Custom

Document Number

8S661FXMTIU-IU

Rev1.0

Date: Thursday, June 16, 2005

Sheet 1 of 33

**Model Name: 8S661FXMTIU-IU**




**Version: 1.0**

## Component value change history

[illegible]




**Circuit or PCB layout change  
for next version**


[illegible]



LGA775A

LGA775
















**Note:**  
VCCA & VCOREPLL  
define doesn't same as  
old P4 design kit

Trace width doesn't  
less than 12 Mil

As close as possible to  
CPU socket

Close to U40(CLOCK Gen.)



Place outside of CPU socket






HOST

SIS661FX/B1[10H]1-040661-20




5.6 GTL\_DET



NB\_HEATSINK[12SP2-04E004-C1\_12SP2-04E004-C2\_12SP2-04E004-C3\_12SP2-04E004-C4]


N.B HEATSINK



| GIGABYTE             |                         |       |         |
|----------------------|-------------------------|-------|---------|
| Title                |                         |       |         |
| SIS661FX-1(HOST/AGP) |                         |       |         |
| Size                 | Document Number         | Rev   |         |
| Custom               | 8S661FXMTIU-IU          | 1.0   |         |
| Date:                | Thursday, June 16, 2005 | Sheet | 7 of 33 |


















For debug mode

TEST POINT

TMODE0  
TMODE1  
TMODE2  
TRAP1  
DLEN-




| GIGABYTE              |                         |       |         |
|-----------------------|-------------------------|-------|---------|
| Title                 |                         |       |         |
| SIS661FX-3(HYPER ZIP) |                         |       |         |
| Size                  | Document Number         | Rev   |         |
| Custom                | 8S661FXMTIU-IU          | 1.0   |         |
| Date:                 | Thursday, June 16, 2005 | Sheet | 9 of 33 |




Power

Close to SIS648 chipset



solder side Cap.











Place on SIS648 chipset  
Solder side.

|          |                         |       |          |
|----------|-------------------------|-------|----------|
| GIGABYTE |                         |       |          |
| File     | SIS661FX-4(POWER)       |       |          |
| Size     | Document Number         | Rev   | 1.0      |
| Custom   | 8S661FXMTIU-JU          |       |          |
| Date     | Thursday, June 16, 2005 | Sheet | 10 of 33 |






Programable on-die pull-high strength for CPU\_S:  
( Infinite, 150, 110, 56 Ohm)






#### SATA use -INTB





IPB\_OUT0 Pull-up: MuTIOL Clock PLL Disable

IPB\_OUT1 Pull-up: MuTIOL V1.0, Default 2.0



| GIGABYTE               |                         |       |          |
|------------------------|-------------------------|-------|----------|
| Title                  |                         |       |          |
| SIS964-3(USB2.0, SATA) |                         |       |          |
| Size                   | Document Number         | Rev   |          |
| Custom                 | 8S661FXMTIU-IU          | 1.0   |          |
| Date:                  | Thursday, June 16, 2005 | Sheet | 13 of 33 |



**Solder side Cap.**

3VDUAL SC150 0.1uF/6V/25V

SB18 SC151 0.1uF/6V/25V



VCC18 SC152 0.1uF/6V/25V

VCC3 SC153 0.1uF/6V/25V


Place on SIS963 chipset  
Solder side.



*DDR SDRAM 1,2*







**For Register  
DDR Support**




|                           |                         |       |            |
|---------------------------|-------------------------|-------|------------|
| <b>GIGABYTE</b>           |                         |       |            |
| Title                     |                         |       |            |
| <b>DDR UNBUFFERED 1,2</b> |                         |       |            |
| Size<br>Custom            | Document Number         |       | Rev        |
|                           | <b>8S661FXMTIU-IU</b>   |       | <b>1.0</b> |
| Date:                     | Thursday, June 16, 2005 | Sheet | 16 of 33   |






### DDRVTT Decouple




每兩個排容之間放一個0603電容  
0.10排容只上10個即可





NOTE: Place these decoupling capacitors close to VTT\_MEM termination resistors. (one decoupling capacitor for each two R-packs)



### DDR25V Decouple



### DDR TERMINATION




VCC : 80 mil





Place 1 at each pair of 3.3V pins

Decoupling capacitors  
(Place near AGP slot)



Place 1 at each pair of VDDQ pins

Place an additional for spread from A14 - A33



**GIGABYTE**


**AGP SLOT**

| Title    |                         |                |
|----------|-------------------------|----------------|
| AGP SLOT |                         |                |
| Size     | Document Number         | Rev            |
| Custom   | 8S661FXMTIU-IU          | 1.0            |
| Date:    | Thursday, June 16, 2005 | Sheet 18 of 33 |




## PRIMARY IDE

963 has internal damping R





963 has internal damping R



These resistor should placed near South Bridge


## SECONDARY IDE

963 has internal damping R




963 has internal damping R


These resistor should placed near South Bridge



Dual Layout with Q12, Q13, ...




## FRONT SIDE USB1






NEAR FRONT USB CONNECTOR

## PCI+IDE RESET



## FUSEVCC, GAMEVCC


NEAR FRONT USB CONNECTOR



| GIGABYTE |                         |                |          |
|----------|-------------------------|----------------|----------|
| IDE, USB |                         |                |          |
| Title    | Document Number         | Rev            | 1.0      |
| Size     | Custom                  | 8S661FXMTIU-IU |          |
| Date:    | Thursday, June 16, 2005 | Sheet          | 20 of 33 |




Dist1: BIOS\_WP  
CH1: BIOS\_WP



BIOS\_WP: BIOS WRITE PROTECT


| PIN | BIOS_WP                |
|-----|------------------------|
| 1-2 | WRITE PROTECT          |
| 2-3 | WRITE ENABLE (default) |






### Filter Cap design:

|                 | Pin-29 | Pin-30 | Pin-31 | Pin-32     |
|-----------------|--------|--------|--------|------------|
| ALC655<br>Rev D | 1000pf | 1000pf | 1uf    | Front-MIC2 |
| ALC655<br>Rev C | 1000pf | 1000pf | 1uf    | X          |
| ALC658          | X      | X      | JD4    | X          |
| ALC650          | 1000pf | 1000pf | 1uf    | 1uf        |
| ALC850          | 1000pf | 1000pf | JD4    | Front-MIC2 |



### Arrangement of Jack detection Pin:

|        | Pin-45(JD0) | Pin-17(JD1)          | Pin-16(JD2)         | Pin-40(JD3)                                   | Pin-31(JD4)                                 | Pin-13(JD5)      |
|--------|-------------|----------------------|---------------------|-----------------------------------------------|---------------------------------------------|------------------|
| ALC655 | for MIC-IN  | for FRONT-OUT        | for LINE-IN         |                                               |                                             |                  |
| ALC658 | for MIC-IN  | for UAJ1             | for UAJ2            | for FRONT-OUT<br>External pull high is needed | for LINE-IN<br>External pull high is needed |                  |
| ALC850 | for MIC-IN  | for Front Pannel OUT | for Front Pannel IN | for FRONT-OUT                                 | for LINE-IN                                 | for SurrBack Out |




|                |                         |                |          |     |
|----------------|-------------------------|----------------|----------|-----|
| GIGABYTE       |                         |                |          |     |
| Title          |                         |                |          |     |
| ALC655/658/850 |                         |                |          |     |
| Size           | Document Number         |                |          | Rev |
| Custom         |                         | 8S661FXMTIU-IU |          | 1   |
| Date:          | Thursday, June 16, 2005 | Sheet          | 24 of 33 |     |




## LINE OUT

JDO,JD2,GPI00 為偵測DEVICE INPUT 時由LOW  
TO HIGH Edge trigger(pop manual)



1/2(3.14)RC=1/2(3.14)8.2K\*4.7U=4.3HZ以上AC 信號全部衰減 TO  
0V 不會造成JDO 誤動作(無device 時play wav )


## MIC




MICROPHONE IN SENSING(當OUTPUT)  
R>4K OHM=>POWER SPEAKER  
4K OHM>R>400 OHM=>MICROPHONE  
R<400 OHM=>HEADPHONE

MICROPHONE IN SENSING(當INPUT)(利用vref 偏壓 與CR43,CR32 並聯求出阻抗)  
7.1k ohm>R>2.3k ohm==>microphone in  
R<2.3k ohm or R>7.1k ohm==>unknown device


## CD IN



## AUX IN




## AC97 JACK





## LINE-IN

LINE IN SENSING(當OUTPUT)  
R>4K OHM=>POWER SPEAKER  
4K OHM>R>400 OHM=>MICROPHONE  
R<400 OHM=>HEADPHONE


LINE IN SENSING(當INPUT)  
swing of input signal>-40dbv(10mv)==>line in  
device active  
swing of input signal<-40dbv(10mv)==>unknown  
line in device



## INTEL FRONT AUDIO



## SPDIF/SPDIF\_IN




| GIGABYTE                |                         |       |          |
|-------------------------|-------------------------|-------|----------|
| Title                   |                         |       |          |
| AUDIO OUTPUT, GAME PORT |                         |       |          |
| Size                    | Document Number         | Rev   |          |
| Custom                  | 8S661FXMTIU-IU          | 1.0   |          |
| Date:                   | Thursday, June 16, 2005 | Sheet | 25 of 33 |


## PROCESSOR HOT

**U-ATX PROCESSOR HOT NO POP**

asserted at 130 degree (RS2=720 ohm)  
deasserted at 115 degree (RS2=1270 ohm)







```
ThermalTake FAN Power Consumption: 0.82A
Intel FAN Power Consumption Spec: 1.1A
```




### CPU\_FAN PIN3,4 CO-LAYOUT

+12V -->40 mils



FRONT PANEL










States for a single-color power LED

| LED States     | ACPI States         | MPD+ | MPD-     |
|----------------|---------------------|------|----------|
| OFF            | S1, S3, S5          | HI   | HI       |
| Steady Green   | S0                  | HI   | LO       |
| Blinking Green | S0(message waiting) | HI   | BLINKING |


States for a dual-color power LED

| LED States      | ACPI States             | MPD+ | MPD-     |
|-----------------|-------------------------|------|----------|
| OFF             | S5                      | HI   | HI       |
| Steady Green    | S0                      | HI   | LO       |
| Blinking Green  | S0(message waiting)     | HI   | BLINKING |
| Steady Yellow   | S1, S3                  | LO   | HI       |
| Blinking Yellow | S1, S3(message waiting) | LO   | BLINKING |


|                  | S0 | S1 | S3 | S5 |
|------------------|----|----|----|----|
| GPI011(GLED-)    | 0  | 1  | 1  | 0  |
| GPI07(SUSLED)    | 0  | B  | B  | 0  |
| ACPILED(Pin A15) | 0  | 0  | 0  | 1  |



PWROK → PWROK 12,15,16,20,28




### 18VDUAL FOR SB & NB




18VDUAL: USB 2.0 unplug, 50mA, each USB 2.0 device add (32~41mA). Maximun load (USB2.0 device\*8) is 327mA.



### VDDQ FOR AGP 4X/8X



### VCC18 FOR NB,SB



### VTT\_GMCHVID FOR 775 CPU




**GIGABYTE**

**VDDQ, VCCVID, 3VDUAL**

| Size   | Document Number | Rev |
|--------|-----------------|-----|
| Custom | 8S661FXMTIU-IU  | 1.0 |

Date: Thursday, June 16, 2005 Sheet 29 of 33

ATX CONN, DC POWER



| 8SRXL South Bridge GPIO LIST |                       |                                     |         |
|------------------------------|-----------------------|-------------------------------------|---------|
| ITEM                         | DESCRIPTION           | STATUS                              | Default |
| GP00                         | Non Use               |                                     | Hi      |
| GP01                         | Non Use               |                                     | Hi      |
| GP04                         | Non Use               |                                     | Hi      |
| GP02                         | Non Use               |                                     | Hi      |
| GP03                         | Green Button          | Hi:Normal, Lo:Into Green mode       | Hi      |
| GPIO5                        | REQ5                  |                                     |         |
| GPIO6                        | GNT5                  |                                     |         |
| GP07                         | Non Use               |                                     | Hi      |
| GP011                        | Non Use               |                                     | Hi      |
| GPi8                         | Wake On Ring          | Hi:Normal, Lo:Ring Power On         | Hi      |
| GPi9                         | Case Open             | Hi:Case Open , Lo:Normal            | Lo      |
| GPi10                        | Clear Caseopen status | Hi:Clear Caseopen Status, Lo:Normal | Lo      |
| GPi13                        | Non Use               |                                     | Hi      |
| GP012                        | Non Use               |                                     | Hi      |
| GPi14                        | Primary Down          | Lo:CODEC Only                       | Lo      |
| GPIO15                       | KB Data               |                                     | Hi      |
| GPIO16                       | KB Clk                |                                     | Hi      |
| GPIO17                       | MS Data               |                                     | Hi      |
| GPIO18                       | MS Clk                |                                     | Hi      |

States for a single-color power LED

| LED States     | ACPI States         | RPO+ | RPO-     | BIOS  |          |
|----------------|---------------------|------|----------|-------|----------|
|                |                     |      |          | GPIO7 | ACPILED  |
| OFF            | S5                  | HI   | HI       | LO    | HI/NC    |
| Steady Green   | S0                  | HI   | LO       | LO    | LO       |
| Blinking Green | S0(message waiting) | HI   | BLINKING | LO    | BLINKING |

States for a dual-color power LED


| LED States      | ACPI States            | RPO+ | RPO-     | BIOS  |          |
|-----------------|------------------------|------|----------|-------|----------|
|                 |                        |      |          | GPIO7 | ACPILED  |
| OFF             | S5                     | HI   | HI       | LO    | HI/NC    |
| Steady Green    | S0                     | HI   | LO       | LO    | LO       |
| Blinking Green  | S0(message waiting)    | HI   | BLINKING | LO    | BLINKING |
| Steady Yellow   | S1,S3                  | LO   | HI       | HI    | HI       |
| Blinking Yellow | S1,S3(message waiting) | LO   | BLINKING | HI    | BLINKING |

States for green LED



| LED States | ACPI States | GLEDP | BIOS   |
|------------|-------------|-------|--------|
|            |             |       | GPIO11 |
| ON         | S1,S3       | HI    | HI     |
| OFF        | S0,S5       | LO    | LO     |

BIOS REQUEST




| SINGLE | DUAL   | INTEL LED DEFINED |         |        |    | GIGABYTE LED DEFINED |         |          |    | SINGLE   | DUAL     |
|--------|--------|-------------------|---------|--------|----|----------------------|---------|----------|----|----------|----------|
|        |        | GPIO7             | ACPILED | GPIO11 |    | GPIO7                | ACPILED | GPIO11   |    |          |          |
| GREEN  | GREEN  | S0                | LO      | LO     | LO | S0                   | LO      | LO       | LO | GREEN    | GREEN    |
| OFF    | YELLOW | S1                | HI      | HI     | HI | S1                   | LO      | BLINKING | HI | G(BLINK) | G(BLINK) |
| OFF    | YELLOW | S3                | HI      | HI     | HI | S3                   | HI      | HI       | HI | OFF      | YELLOW   |
| OFF    | OFF    | S4/S5             | LO      | HI/NC  | LO | S4/S5                | LO      | HI/NC    | LO | OFF      | OFF      |



| GIGABYTE       |                         |                |         |
|----------------|-------------------------|----------------|---------|
| Title          |                         |                |         |
| ATX, GPIO LIST |                         |                |         |
| Size Custom    | Document Number         | 8S661FXMTIU-IU | Rev 1.0 |
| Date:          | Thursday, June 16, 2005 | Sheet 30       | of 33   |





-SUSB: S3=Low  
-SUSB: S0, S1, S5=Hi



OVDDR267, OVDDR27V RESUME WELL  
DEFAULT HIGH

|      | GPIO13<br>OVDDR27V | GPIO1<br>OVDDR26V |
|------|--------------------|-------------------|
| 2.5V | HIGH               | HIGH              |
| 2.6V | LOW                | HIGH              |
| 2.7V | LOW                | LOW               |









# VGA CONNECTOR 1

SIS 648(FX) NO POP



% PLEASE PLACE THESE COMPONENTS AS NEAR VGA CONNECT AS POSSIBLE

22P/4/N/50V 22P/4/N/50V 22P/4/N/50V 10P/4/N/50V 10P/4/N/50V 10P/4/N/50V



REV 0.2 VGA GND GUARD

DUAL LAYOUT(VGA/COM)

|               |                         |       |          |
|---------------|-------------------------|-------|----------|
| GIGABYTE      |                         |       |          |
| Title         |                         |       |          |
| VGA CONNECTOR |                         |       |          |
| Size          | Document Number         | Rev   | 1.0      |
| B             | 8S661FXMTIU-IU          |       |          |
| Date:         | Thursday, June 16, 2005 | Sheet | 33 of 33 |