

Cover Sheet	1
Block Diagram	2
AMD 462pins SocketA CPU - Signals	3
AMD 462pins SocketA CPU - Power	4
CRUSH17/18 - Host & VID Signals	5
CRUSH17/18 - Memory-A & LDT & PLL Signals	6
CRUSH17/18 - Memory-B Signals	7
CRUSH17/18 - AGP & VIDEO Signals	8
MCP2 - CPU & PCI & LDT & IDE Signals	9
MCP2 - MAC & USB & LPC & AC'97 Signals	10
LPC I/O - W83627HF	11
AC97 Audio - ALC202A	12
MII LAN & LPC Flash EEPROM	13
DDR System Memory	14
AGP 3.0 Slot, LDT Regulator & COM2	15
PCI Slots	16
ATA33/66/100 IDE & Video Connectors	17
FAN & USB Connectors	18
I1394 PHY & Connectors	19
ATX & Front Panel	20
ACPI (MS5) Controller	21
VRM 9.0 - ST6917B	22
GPIO	23
Power Delivery Map & MANUAL	24
Revision History 1	25

(MS-6595) *Version: 0B*

Nvidia (R) Crush17/18(nForce IGP 64) + MCP2/2H Chipset
AMD Althon/Duron/Morgan/Palomino Socket 462 Processor
CPU:

AMD Duron/Morgan 1.2G&1.3G
AMD Althon/Palomino 1500 - 1.333G/266MHz
AMD Althon/Palomino 1600 - 1.400G/266MHz
AMD Althon/Palomino 1700 - 1.467G/266MHz
AMD Althon/Palomino 1800 - 1.533G/266MHz
AMD Althon/Palomino 1900 - 1.600G/266MHz
AMD Althon/Palomino 2000 - TBD

System Chipset:

Nvidia nForce IGP 64 (North Bridge)
MCP2/2H Wep (South Bridge)

On Board Chipset:

BIOS -- LPC EEPROM
AC'97 Codec -- ALC202A
LPC Super I/O -- W83627HF-AW
LAN -- ICS1893 PHY
I1394 -- FW803 PHY

Expansion Slots:

AGP 3.0 SLOT * 1
PCI2.2 SLOT * 3


PWM Controller:

ST6917B


ACPI:

MS5

 MICRO-STAR INT'L CO., LTD.			
Title COVER SHEET			
Size	Document Number (MS-6595)		Rev DA
Date: Monday, July 08, 2002	Sheet	1	of 25




CPU SIGNAL BLOCK




****All CPU interface are 2.5V tolerant****


CPU PULL-UP / DOWN BLOCK




CPU K7 EMI termination




CPU SYSCLK BLOCK



CPU Clock Multiplier




CPU K7CLKOUT BLOCK




***Trace lengths of CLKOUT and CLKOUT# are between 2" and 3"**


CPU SYSCLK REFERENCE BLOCK



CPU ZN / ZP BLOCK




CPU APIC BLOCK




MICRO-STAR INT'L CO., LTD.

Title		AMD Socket462 CPU (Signal)	
Size	Document Number	Rev OA	
(MS-6597)			
Date	Monday, July 08, 2002	Sheet	3 of 25

CPU VOLTAGE BLOCK




CPU DECOUPLING CAPACITORS



CPU PLL VOLTAGE BLOCK

(40mils trace / 60 mils space)



MICRO-STAR INT'L CO., LTD.			
Title: AMD Socket462 CPU (Power)			
Size	Document Number	Rev	
	(MS-6597)	0B	
Date: Monday, July 08, 2002	Sheet	4	of 25


CRUSH 18 HOST SIGNALS

BELONG TO CLKFWD GROUP[SADDIN] MATCH W/IN +/-10MILS OF GROUP 5/15, CLK:10/30
 BELONG TO CLKFWD GROUP[SADDOUT] MATCH W/IN +/-10MILS OF GROUP 5/15, CLK:10/30
 BELONG TO CLKFWD GROUP;MATCHED TO INDIVIDUAL CLKFWD GROUP
 RESPECTIVELY.[SDATA0], [SDATA1], [SDATA2],[SDATA3] W/IN+/-10MILS OF GROUP


CRUSH18

PART 1

HOST INTERFACE




SYSTEM DATA-IN-CLK NOISE L/C BLOCK




CLK must less DATA 1.5inches
(Place in middle of Bus)


VID Selector Block




C18 Decoupling Caps




Place close to C18




C18 VREF Volatge





S3 Delay Block





FSB Selection











CRUSH 18 AGP & VIDEO SIGNALS




TV OUT Circuit







MCP2 MAC, USB, 1394A, LPC & AC'97 SIGNALS



MCP2 PULL-UP & DOWN RESISTORS




Battery




CMOS CLEAR JUMPER

JBAT1	CMOS Status
1 - 2	Normal
2 - 3	Clear CMOS

PASSWORD CLEAR JUMPER




MCP2 USB & USB2 BLOCK



MICRO-STAR INT'L CO., LTD.


Title: MCP CPU & IDE & LPC & MAC & USB Signals
Size: Document Number (MS-6595)
Date: Monday, July 08, 2002 Sheet 10 of 25

FLOPPY CONNECTOR




Title			
LPC SUPER I/O & CONNECTORS			
Size	Document Number		Rev
	(MS-695)		QA
Date	Monday, July 08, 2002	Sheet	11 of 25


AC'97 AUDIO CODEC




SPDIF CONNECTOR




INTERNAL SPEAKER




AUDIO CODE CRYSTAL CIRCUIT




COPPER




AUDIO CODE REGULATORS



FRONT AUDIO



CD IN




AUX IN




MICRO-STAR INT'L CO., LTD.

Title	AC97 AUDIO		
Size	Document Number	(MS-6595)	Rev
Date	Monday, July 08, 2002	Sheet	12 of 25


AGP 3.0 4X/8X SLOT



LDT Voltage Regulator




SERIAL PORT 2




PCI SLOT 1 (PCI VER: 2.2 COMPLY)

PCI SLOT 2 (PCI VER: 2.2 COMPLY)


PCI SLOT 3 (PCI VER: 2.2 COMPLY)



IDSEL = AD22
MASTER = PREQ#0
PIRQ#A




IDSEL = AD23
MASTER = PREQ#1
PIRQ#D




IDSEL = AD24
MASTER = PREQ#2
PIRQ#C

IDSEL = AD25
SLAVE = PREQ#3
PIRQ#B

PCI PULL-UP / DOWN RESISTORS




PCI SLOT DECOUPLING CAPACITORS



MICRO-STAR INT'L CO., LTD.	
Title	PCI 1 & 2 & 3 Slots
Size	Document Number (MS-6595)
Date	Monday, July 08, 2002
Sheet	16 of 25


PRIMARY IDE BLOCK



All series resistors close to MCP2 within 500 mils.


PCB layout for a VGA-to-DVI converter. The layout shows a central YCN15F-003-1 converter chip connected to a DVI connector (CN8) and a VGA connector. Power planes are color-coded: RED for VCC3, GREEN for VCC2, and BLUE for VCC1. Each plane has a "rounded GND" section with decoupling capacitors (C189, C190, C200, C201, C233, C238, C244, C245) and resistors (R227, R233, R236, R252, R254, R256). The VGA connector has clamping diodes (D10, D11) and a note to place clamping diodes close to the VGA connector. The DVI connector has a note to connect each routed GND to the GND plane at one point only (one via).

Close to VGA Conn.




Size	Document Number	Rev
	(MS-6595)	QA
Date:	Monday, July 08, 2002	Sheet 17 of 25


POWER CIRCUIT FOR LAN USB PORT 4,5




POWER CIRCUIT FOR I1394 USB PORT 0,1




POWER CIRCUIT FOR USB PORT 0,1,2,3




FRONT PANEL USB CONNECTOR FOR USB PORT 4,5




REAR PANEL LAN_USB CONNECTOR FOR USB PORT 2,3




REAR PANEL I1394 USB CONNECTOR FOR USB PORT 0,1



CPU FAN




SYSTEM FAN




MICRO-STAR INT'L CO., LTD. HW Project Leader : Joey Lee HW Project Engineer : Richard Shih			
Title: FAN & USB Connectors			
Size	Document Number		Rev
	(MS-6595)		0A
Date: Monday, July 08, 2002	Sheet 18 of 25		

ATX Connector




Front Panel




Simulation




Internal Ring Wake Up Block




BUZZER




RSMRST#



IDE LED



UNUSE LOGIC




MICRO-STAR INT'L CO., LTD.			
Title: ATX Connector & Front Panel			
Size:	Document Number: (MS-6595)		Rev: 0A
Date: Monday, July 08, 2002	Sheet: 20	of: 25	


ACPI (MS5)

SEL0	5VUSB
H	2 MOSFET
L	1 MOSFET


```
**S50# pin function(Hi level = 5V)
same as 5VUSB(Hi level = 12V)
```




System Decoupling Capacitors



2.5V POWER TRANSLATOR



Discharge Residual Voltage



MICRO-STAR INT'L CO., LTD.

Title	System & DDR Regulators
-------	-------------------------


(MS-6595)

Date: Monday, July 08, 2002 Sheet 21 of

2	1
---	---




Require this connection as a copper pour.



VID4	VID3	VID2	VID1	VID0	VDC(V)
1	1	1	1	0	1.100
1	1	1	0	1	1.125
1	1	1	0	0	1.150
1	1	0	1	1	1.175
1	1	0	1	0	1.200
1	1	0	0	1	1.225
1	1	0	0	0	1.250
1	0	1	1	1	1.275
1	0	1	1	0	1.300
1	0	1	0	1	1.325
1	0	1	0	0	1.350
1	0	0	1	1	1.375
1	0	0	1	0	1.400
1	0	0	0	1	1.425
1	0	0	0	0	1.450
0	1	1	1	1	1.475

VID4	VID3	VID2	VID1	VID0	VDC(V)
0	1	1	1	0	1.500
0	1	1	0	1	1.525
0	1	1	0	0	1.550
0	1	0	1	1	1.575
0	1	0	1	0	1.600
0	1	0	0	1	1.625
0	1	0	0	0	1.650
0	0	1	1	1	1.675
0	0	1	1	0	1.700
0	0	1	0	1	1.725
0	0	1	0	0	1.750
0	0	0	1	1	1.775
0	0	0	1	0	1.800
0	0	0	0	1	1.825
0	0	0	0	0	1.850
1	1	1	1	1	OFF

ATX12V POWER CONNECTOR



MICRO-STAR INT'L CO., LTD.			
Title: VRM9.0 - ST6917B			
Size:	Document Number:		Rev: 0A
		(MS-6595)	
Date:	Monday, July 08, 2002	Sheet:	22 of 25

MCP2

GPIO Pin	Type	Function
GPIO 0	I	PCI_REQ#4 (multifunction pin)
GPIO 1	O	PCI_GNT#4 (multifunction pin)
GPIO 2	I/O	PCI_PERR# (multifunction pin)
GPIO 3	I	PCI_IRQ#E (multifunction pin)
GPIO 4	I	MII_RXER (multifunction pin)
GPIO 5	I	Pull up through 8.2K ohms (LPC_DRQ#1)
GPIO 6	I	USB_OC1# (multifunction pin)
GPIO 7	I	USB_OC2# (multifunction pin)
GPIO 8	I	USB_OC2# (multifunction pin)
GPIO 9	I	USB_OC3# (multifunction pin)
GPIO 10	I	USB_OC3# (multifunction pin)
GPIO 11	O	AC_SDIN1 (multifunction pin)
GPIO 12	I	A20GATE (multifunction pin)
GPIO 13	I	Pull up through 10K ohms (SPDIF)
GPIO 14	I/O	Unused
GPIO 15	I/O	B_SEL0
GPIO 16	I/O	B_SEL1
GPIO 17		Reserve
GPIO 18	I/O	Unused
GPIO 19	I	SIO_PME# (multifunction pin)
GPIO 20	O	SLP_S1# (multifunction pin)
GPIO 21	I	Pull up through 4.7K ohms (SIO_SMI#)
GPIO 22	I	THERM# (multifunction pin)
GPIO 23	I	INTRUDER#
GPIO 24	I	RI# (multifunction pin)
GPIO 25	I	KBRST# (multifunction pin)
GPIO 26	O	SUSCLK (multifunction pin)
GPIO 27	I	AGP_PME# (multifunction pin)
GPIO 28	I	Primary IDE ATA66/100 detection (ATADET0)
GPIO 29	I	GPIO29 (Clear password indicator , Active Low)
GPIO 30	I	Secondary IDE ATA66/100 detection (ATADET1)
GPIO 31	I	GPIO31 (CMOS Clear , Active Low)
GPIO 32	O	Unused
GPIO 33	O	Unused
GPIO 34	O	Unused
GPIO 35	I	Unused
GPIO 36~38	I	Pull up through 10K ohms to 3VDUAL
GPIO 48	I	Pull up through 4.7K ohms to VCC3
GPIO 49	I	Pull up through 4.7K ohms to VCC3
SPIO 0	I/O	SM_CLK0 (multifunction pin)
SPIO 1	I/O	SM_DATA0 (multifunction pin)
SPIO 2	I/O	SM_CLK1 (multifunction pin)
SPIO 3	I/O	SM_DATA1 (multifunction pin)
SPIO 4	I/O	DDC_CLK (multifunction pin)
SPIO 5	I/O	DDC_DATA (multifunction pin)
SPIO 6	I	Pull up through 4.7K ohms (SMB_ALERT#)

PCI Config.

DEVICE	MCP1 INT Pin	REQ# / GNT#	IDSEL	CLOCK	CLK GEN PIN OUT
PCI Slot 1	INTA# INTB# INTC# INTD#	PCI_REQ#0 PCI_GNT#0	AD22	PCICLK0	MCP/AB20 (PCI_CLK0)
PCI Slot 2	INTD# INTA# INTB# INTC#	PCI_REQ#1 PCI_GNT#1	AD23	PCICLK1	MCP/AB18 (PCI_CLK1)
PCI Slot 3	INTC# INTD# INTA# INTB#	PCI_REQ#2 PCI_GNT#2	AD24	PCICLK2	MCP/AB12 (PCI_CLK2)

LPC Super I/O

GPIO Pin	Type	Function
GPIO 10	O	MB_ID2
GPIO 11	O	Unused
GPIO 12	O	Unused
GPIO 13	O	Unused
GPIO 14	O	MB_ID0
GPIO 15	O	MB_ID1
GPIO 16	O	Unused
GPIO 17	O	MB_ID3
GPIO 20	O	Unused
GPIO 21	I	SMBCLK
GPIO 22	I/O	SMBDATA
GPIO 23	O	Unused
GPIO 24	O	Unused
GPIO 25	I	BIOS Protect , Active Low
GPIO 26	O	Unused
GPIO 27	O	Floppy Driven Density Select , Active Low
GPIO 30	I	SLP_S3#
GPIO 31	O	PS_ON#
GPIO 32	O	Unused
GPIO 33	O	Unused
GPIO 34	O	PWR_FAN , High to turn ONFAN
GPIO 35	O	Unused

Flash ROM


GPIO Pin	Type	Function
GPI 0	I	Pull down through 1K ohms (unused)
GPI 1	I	Pull down through 1K ohms (unused)
GPI 2	I	Pull down through 1K ohms (unused)
GPI 3	I	Pull down through 1K ohms (unused)
GPI 4	I	Pull down through 1K ohms (unused)

DDR DIMM Config.


DEVICE	ADDRESS	CLOCK
DIMM 2	1010010B	MCLK_A0/MCLK_A0# MCLK_A1/MCLK_A1# MCLK_A2/MCLK_A2#
DIMM 1	1010001B	MCLK_B0/MCLK_B0# MCLK_B1/MCLK_B1# MCLK_B2/MCLK_B2#

		MICRO-STAR INT'L CO., LTD.	
Title		General Purpose Spec	
Size	Document Number	(MS-6595)	Rev 0A
Date	Monday, July 08, 2002	Sheet	23 of 25


Power Delivery Map




Mounting Holes



Location Reference Hold



Auto-BOM Manual Parts



MICRO-STAR INT'L CO., LTD.			
Title			
POWER DELIVERY MAP & MANUAL			
Size	Document Number	Rev	
	(MS-6597)	OB	
Date:	Monday, July 08, 2002	Sheet	24 of 25



Title			
REVISION HISTORY - 1			
Size	Document Number		Rev
	(MS-6595)		QA
Date	Monday, July 08, 2002		Sheet 25 of 25