

MS-6712F1 *Version 2.0B*

VIA (R) KT400 VT8377 Chipset
Palamino/Mogan 462pin cPGA Processor Schematics


- *AMD PGA 462 Processor
- *VIA KT400 / VT8235 Chipset
(DDR 400 / AGP 8X / VLink 8X)
- *Winbond 83697HF-VF LPC I/O
- *VT6103 Fast Ethernet 10 / 100
- *AC'97 Codec ALC202A/ALC650
- *USB 2.0 support (integrated into VT8235)
- *Jump Less support

MS-6712F1 ver:2.0B			
Option L BOM (with LAN)			
	SMT 5010	785	
	SMT 5020	19	
	DIP	60	72
Total		878	
Standard BOM (without LAN)			
	SMT 5010	XXX	
	SMT 5020	XX	
	DIP	60	XX
Total		XXX	

Title	Page
Cover Sheet	1
Block Diagram	2
GPIO SPEC	3
AMD 462 PGA Socket	4,5
Clock Synthesizer	6
KT400	7,8,9,10
System Memory	11,12,13
DDR Terminations	14
AGP SLOT	15
VT8235	16,17,18
PCI Connectors	19,20
CNR RISER / DLED	21
AC'97 Codec & Audio connector	22
ATA 66/100 Connectors	23
Ethernet LAN	24
Front USB Port & Rear USB Port	25
LPC I/O	26
H/W monitor;Fan; Thermal Protection	27
I/O Connectors	28
HIP 6302	29
CPU Ratio / Vcore / LED Setting	30
MS-5 ACPI POWER	31
Front Panel; PowerOK Circuit	32
BULK / Decoupling	33
HISTORY	34

Orcad Config	ERP BOM	Function Description	
6712F1-20B-L	601-6712-060	MS-6712F1 20B MSI Option:L	With LAN. Without CNR. MSI Standard
		MS-6712F1 20B MSI Standard	Without LAN. MSI Standard

Block Diagram



GPIO FUNCTION

VT8233 GPIO Function Define

PIN NAME	Function define
GP00 (VSUS33)	GP00
GP01/SUSA#(VSUS33)	SUSA#
GP02/SUSB#(VSUS33)	SUSB#
GP03/SUSST1#(VSUS33)	SUSST1#
GP04/SUSCLK(VSUS33)	SUSCLK
GP05/CPUSTP#	CPUSTP#
GP06/PCISTP#	PCISTP#
GP07/SLP#	SLP#
GP08/GPI8/IPBIN0	Exteranl Pull up to VCC3
GP09/GPI9/IPBIN1	Exteranl Pull up to VCC3
GP010/GPI10/IPBRDFR	GPI10(PRI_DOWN)
GP011/GPI11/IPBRDCK	
GP012/GPI12/IPBOUT0	GP012
GP013/GPI13/IPBOUT1	GP013
GP014/GPI14/IPBTDFR	GP014
GP015/GPI15/IPBTDCCK	GP015
GP016/SA16/STRAP	CPU FID0 Strapping
GP017/SA17/STRAP	CPU FID1 Strapping
GP018/SA18/STRAP	CPU FID2 Strapping
GP019/SA19/STRAP	CPU FID3 Strapping
GP020/GPI20/ACSDIN2/PCS0#/EI	GP020
GP021/GPI21/ACSDIN3/PCS1#/SLPBTN#	GP021
GP022/GPI22/IOR#	GP022
GP023/GPI23/IOW#	GP023
GP024/GPI24/GPI0A	
GP025/GPI25/GPI0C	
GP026/GPI26/SMBDT2(VSUS33)	SMBDATA2/Slave SMBUS
GP027/GPI27/SMBCK2(VSUS33)	SMBCLK2/Slave SMBUS
GP028/GPI28/APICD0/APICCS#	
GP029/GPI29/APICD1/APICACK#	
GP030/GPI30/GPI0D	
GP031/GPI31/GPI0E	

PIN NAME	Function define
GPI0	GPI0
GPI1	ATADET0=>Detect IDE1 ATA100/66
GPI2/EXTSMI#	EXTSMI#
GPI3/RING#	RING#
GPI4/LID#	ATADET1=>Detect IDE2 ATA100/66
GPI5/BATLOW#	Exteranl Pull up to 3VDUAL
GPI6/PME#	PME#
GPI7/SMBALRT#	Exteranl Pull up to 3VDUAL
GPI16/INTRUDER#	Exteranl Pull down
GPI17/CPUMISS	Exteranl Pull up to 3VDUAL
GPI18/AOLGP1/THRM#	THRM#
GPI19/IORDY	Exteranl Pull up to VCC3













DDR Voltage	SET1	SET2
2.5V	1	1
2.6V	0	1
2.7V	1	0
2.8V	0	0

PCI

DEVICES	INT#	IDSEL	REQ#/GNT#	CLOCK
PCI SLOT 1	INT#A INT#B INT#C INT#D	AD16	PREQ#1 PGNT#1	PCICLK1
PCI SLOT 2	INT#B INT#C INT#D INT#A	AD17	PREQ#2 PGNT#2	PCICLK2
PCI SLOT 3	INT#C INT#D INT#A INT#B	AD18	PREQ#3 PGNT#3	PCICLK3
PCI SLOT 4	INT#D INT#A INT#B INT#C	AD19	PREQ#4 PGNT#4	PCICLK4
PCI SLOT 5	INT#B INT#C INT#D INT#A	AD21	PREQ#5 PGNT#6	PCICLK5
PCI SLOT 6	INT#C INT#D INT#A INT#B	AD22	PREQ#0 PGNT#0	PCICLK6

SOCKET 462 Part 1

All CPU interface are 2.5V tolerant




* Trace lengths of CLKOUT and -CLKOUT are between 2" and 3"

Micro Star Restricted Secret		
Title	SOCKET 462 Part 1	Rev
Document Number	MS-6712	20A
MICRO-STAR INT'L No. 68, 11 De St. Jung-He City, Taippei Hsien, Taiwan http://www.msi.com.tw		
Last Revision Date: Friday, November 08, 2002		
Sheet 4 of 34		

SOCKET 462 Part 2

Power supply from MS-5





Used when
spec.
change

VCCA_PLL trace length from the VR1 to the PGA must be 0.75".


Place all filters close to the PGA.

Keep all power and signal trace away from the VR1.







Place a cut in the GND plane around the VCCA_PLL regulator circuit.



For 166MHz power
strapping
SB and CLK Gen
166MHz
strapping



FID[3:0]	Clock Multiplier	FID[3:0]	Clock Multiplier
0000	11.0	1000	7.0
0001	11.5	1001	7.5
0010	12.0	1010	8.0
0011	12.5	1011	8.5
0100	5.0	1100	9.0
0101	5.5	1101	9.5
0110	6.0	1110	10.0
0111	6.5	1111	10.5



For AMD CPU Thermal protection

Micro Star Restricted Secret

Title SOCKET 462 Part 2		Rev 20A
Document Number MS-6712		
MICRO-STAR INT'L No. 68, 4th De St, Jung-Hs City, Taipei Hsien, Taiwan http://www.msi.com.tw		Last Revision Date: Friday, November 08, 2002
Sheet		5 of 34

Frequency strapping

1 1 1 1 0	for 100MHz(default)
1 1 1 1 1	for 133MHz
1 1 1 0 1	for 166MHz


Adjust other Frequency by BIOS.




Frequency strapping	
1 1 1 1 0	for 100MHz(default)
1 1 1 1 1	for 133MHz
1 1 1 0 1	for 166MHz
Adjust other Frequency by BIOS	

Adjust other Frequency by BIOS


Micro Star Restricted Secret

Title <i>Clock Synthesizer</i>		Rev
Document Number <i>MS-6712</i>		20A
MICRO-STAR INT'L No. 69, 1 st Fl. De St. Jung-He City, Taipei Hsien, Taiwan http://www.msi.com.tw		Last Revision Date: Friday, November 08, 2002 Sheet 6 of 34






For VIA KT400








Place resistors as close as to NB; Length is 2.5"-3".




Place as close as to VT8366

Micro Star Restricted Secret		
Title	VT8377 Memory	Rev 20A
Document Number	MS-6712	
MICRO-STAR INT'L No. 68, De St. Jung-He City, Taippei Hsien, Taiwan http://www.msi.com.tw		Last Revision Date: Friday, November 08, 2002
Sheet	8	of 34






close to KT400 power pin




Micro Star Restricted Secret		
Title	VT8377 POWER	Rev 20A
Document Number	MS-6712	
MICRO-STAR INT'L No. 6B, 14 De St, Jung-He City, Taipen Hsien, Taiwan http://www.msi.com.tw		Last Revision Date: Friday, November 08, 2002 Sheet 10 of 34

Place 104p Cap. near the DIMM










SYSTEM MEMORY




Micro Star Restricted Secret		
Title	System Memory : DDR DIMM 3	Rev 20A
Document Number	MS-6712	
MICRO-STAR INT'L No. 68, 1st De St, Jung-He City, Taipei Hsien, Taiwan http://www.msi.com.tw		Last Revision Date: Friday, November 08, 2002 Sheet 13 of 34

DDR Terminations




Place these decoupling capacitors close to VTT_DDR termination resistors.
One decoupling capacitor for each R-pack.




Micro Star Restricted Secret		
Title	DDR Terminations	Rev
Document Number	MS-6712	20A
MICRO-STAR INT'L No. 6, De St. Jung-He City, Taipai Hsien, Taiwan http://www.msi.com.tw		
Last Revision Date: Friday, November 08, 2002		
Sheet 14 of 34		

AGP PRO Connector




Add-in Card Power				
	I _{max}	V _{Min}	V _{Max}	Units
VDDQ	2.0A	1.425	1.575	V
VCC3	6.0A	3.15	3.45	V
3VDUAL	0.75A	3.15	3.45	V
VCC5	2.0A	4.75	5.25	V
VCC12	1.0A	11.4	12.6	V




Micro Star Restricted Secret		
Title	AGP PRO Slot	Rev 20A
Document Number	MS-6712	
MICRO-STAR INT'L No. 6, De St. Jung-He City, Taipen Hsien, Taiwan http://www.msi.com.tw		Last Revision Date: Friday, November 08, 2002 Sheet 15 of 34





Micro Star Restricted Secret		
Title	VT8235 Part 1	Rev 20A
Document Number	MS-6712	
MICRO-STAR INT'L No. 66, Hsin-De St., Jung-He City, Taipei Hsien, Taiwan http://www.msi.com.tw		Last Revision Date: Friday, November 08, 2002
Sheet	16	of 34








PCI Connectors



PCI BUS




CNR Riser / DELD




Micro Star Restricted Secret		
Title	CNR Riser	Rev
Document Number	MS-6712	20A
MICRO-STAR INT'L No. 99, Hsin-De St, Jung-He City, Taipei Hsien, Taiwan http://www.msi.com.tw		Last Revision Date: Friday, November 08, 2002
Sheet	21	of 34

ATA 33/66/100 Connector







PRIMARY IDE CONN.



SECONDARY IDE CONN.




For 100/133/166 power strapping













Micro Star Restricted Secret		
Title	ATA 33/66/100 Connector	Rev
Document Number	MS-6712	20A
MICRO-STAR INT'L		
No. 68, 11 De St, Jung-He City,		
Taipei Hsien, Taiwan		
http://www.msi.com.tw		
Last Revision Date: Friday, November 08, 2002		
Sheet	23	of 34

Fast Ethernet 1-Port PHY




Micro Star Restricted Secret		
Title	Fast Ethernet /1-Port PHY	Rev
Document Number	MS-6712	20A
MICRO-STAR INT'L No. 66, Hu De St, Jung-He City, Taipei Hsien, Taiwan http://www.msi.com.tw		Last Revision Date: Friday, November 08, 2002
Sheet	24	of 34

FRONT USB PORT




Micro Star Restricted Secret		
Title	Front USB Port	Rev
Document Number	MS-6712	20A
MICRO-STAR INT'L No. 6, De St. Jung-He City, Taippei Hsien, Taiwan http://www.msi.com.tw		Last Revision Date: Friday, November 08, 2002
Sheet		25 of 34


Super I/O






FLOPPY DISK HEADER





SIO



Chassis Intrusion Header




Distribute near the VCC power pin of the LPC



Micro Star Restricted Secret		
Title	Winbond W697HF	Rev
Document Number	MS-6712	20A
MICRO-STAR INT'L No. 68, De St. Jung-He City, Taipei Hsien, Taiwan http://www.msi.com.tw		Last Revision Date: Friday, November 08, 2002
Sheet		26 of 34


AMD CPU Thermal Protection Circuit

AMD Thermal protection




Hardware Monitor





Fan Speed Control



SYSTEM ROM




Micro Star Restricted Secret		
Title	Hardware Monitor	Rev
Document Number	MS-6712	20A
MICRO-STAR INT'L No. 66, Sec. 2, De St. Jung-He City, Taipei Hsien, Taiwan http://www.msi.com.tw		Last Revision Date: Friday, November 08, 2002
Sheet		27 of 34



Micro Star Restricted Secret		
Title	LPT / COM Port	Rev
Document Number	MS-6712	20A
MICRO-STAR INT'L No. 66, De St. Jung-He City, Taipei Hsien, Taiwan http://www.msi.com.tw		Last Revision Date: Friday, November 08, 2002
Sheet	28	of 34


Voltage Regular Module



V4D	V3D	V2D	V1D	V0D	VDC(V)
1	1	1	1	0	1.100
1	1	1	0	1	1.125
1	1	1	0	0	1.150
1	1	0	1	1	1.175
1	1	0	1	0	1.200
1	1	0	0	1	1.225
1	1	0	0	0	1.250
1	0	1	1	1	1.275
1	0	1	1	0	1.300
1	0	1	0	1	1.325
1	0	1	0	0	1.350
1	0	0	1	1	1.375
1	0	0	1	0	1.400
1	0	0	0	1	1.425
1	0	0	0	0	1.450
0	1	1	1	1	1.475

V4D	V3D	V2D	V1D	V0D	VDC(V)
0	1	1	1	0	1.500
0	1	1	0	1	1.525
0	1	1	0	0	1.550
0	1	0	1	1	1.575
0	1	0	1	0	1.600
0	1	0	0	1	1.625
0	1	0	0	0	1.650
0	0	1	1	1	1.675
0	0	1	1	0	1.700
0	0	1	0	1	1.725
0	0	1	0	0	1.750
0	0	0	1	1	1.775
0	0	0	1	0	1.800
0	0	0	0	1	1.825
0	0	0	0	0	1.850
1	1	1	1	1	OFF

POWER OK Circuits




Micro Star Restricted Secret		
Title	Power OK Circuits	Rev 20A
Document Number	MS-6712	
MICRO-STAR INT'L No. 68, Sec. 4, De St. Jung-He City, Taippei Hsien, Taiwan http://www.msi.com.tw		Last Revision Date: Friday, November 08, 2002
Sheet	31	of 34

BULK / Decoupling


CPU

Place on SOCKET 462 Cavity




VT8377


Place on VT8366 Solder side




DDR



For EMI



for EMI, place these cap to PCI 3,4 / 91.9.26



Micro Star Restricted Secret		
Title	BULK / Decoupling	Rev
Document Number	MS-6712	20A
MICRO-STAR INT'L No. 68, De St. Jung-He City, Taipen Hsien, Taiwan http://www.msi.com.tw		
Last Revision Date: Friday, November 08, 2002		Sheet
		32 of 34

1.0 Revision History (Changes from Rev 0A)

Sheet	Desciption
4	Add LCL Filter for -DICKx Signals.
15	Change EC2,EC27 Package for 1000u/6.3V.
16	Change Fan Control Logic.
19	Add Input Capacitor EC36 for meet future SPEC.
	Implement PC2001 SPEC for Future.

2.0 Revision History (Changes from Rev 1.0)

Sheet	Desciption
23	Change IDE1 & IDE2 Location.
25	Add Front USB Connector Circuit to share with USB1.

2.0A Revision History (Changes from Rev 2.0)

Sheet	Desciption
5	Remove MS3 OverClock Circuit and use AMD Standard SPEC.
5	Implement AMD FSB 133/166 Auto Sense Function for Future.
22	Add Resistor for Front & Rear Line-Out connected.
	Remove Short line between Common Choke by EMI Request.

Micro Star Restricted Secret		
Title	History	Rev 20A
Document Number	MS-6712	
MICRO-STAR INT'L No. 68, 1st De St, Jung-He City, Taipei Hsien, Taiwan http://www.msi.com.tw	Last Revision Date: Friday, November 08, 2002	
	Sheet	33 of 34



VBAT1_BAT
BAT-B-CR2032-P-3V-220mAh

PCB1
P01-6712208-K10
P01-6712208-K10

U7-FAN1
MSI
DDR
X_HEATSINK
E32-0400290-A58

U7-HS1
MSI
DDR
HEATSINK
E31-0400070-A02

CPU1-P
PAD

SW1(1-2)
YJUMPER-MG

SW2(1-2)
YJUMPER-MG

JP1(1)
X_YJUMPER-MG

JBAT1(1-2)
YJUMPER-MG

HQ23
MOSHS

HQ26
MOSHS

JSP3_X
YJ103-B
N32-1030071-H06

JCOM1
COM-D9-GN

JCOM2
COM-D9-GN

Micro Star Restricted Secret		
Title	Packing Bom	Rev 20A
Document Number	MS-6712	
MICRO-STAR INT'L No. 68, 1st De St, Jung-He City, Taipei Hsien, Taiwan http://www.msi.com.tw	Last Revision Date: Friday, November 08, 2002 Sheet 34 of 34	